

COMMANDS MANUAL

P3

CUSTOM[®]

CUSTOM S.p.A.
Via Berettine 2/B
43010 Fontevivo (PARMA) - Italy
Tel. : +39 0521-680111
Fax : +39 0521-610701
http: www.custom.biz

Customer Service Department:
www.custom4u.it

© 2021 CUSTOM S.p.A. – Italy.

All rights reserved. Total or partial reproduction of this manual in whatever form, whether by printed or electronic means, is forbidden. While guaranteeing that the information contained in it has been carefully checked, CUSTOM S.p.A. and other entities utilized in the realization of this manual bear no responsibility for how the manual is used. Information regarding any errors found in it or suggestions on how it could be improved are appreciated. Since products are subject to continuous check and improvement, CUSTOM S.p.A. reserves the right to make changes in information contained in this manual without prior notification.

The pre-installed multimedia contents are protected from Copyright CUSTOM S.p.A. Other company and product names mentioned herein may be trademarks of their respective companies. Mention of third-party products is for informational purposes only and constitutes neither an endorsement nor a recommendation. CUSTOM S.p.A. assumes no responsibility with regard to the performance or use of these products.

THE IMAGES USED IN THIS MANUAL ARE USED AS AN ILLUSTRATIVE EXAMPLES. THEY COULDN'T REPRODUCE THE DESCRIBED MODEL FAITHFULLY.

UNLESS OTHERWISE SPECIFIED, THE INFORMATION GIVEN IN THIS MANUAL ARE REFERRED TO ALL MODELS IN PRODUCTION AT THE ISSUE DATE OF THIS DOCUMENT.

GENERAL INSTRUCTIONS

CUSTOM S.p.A. declines all responsibility for accidents or damage to persons or property occurring as a result of tampering, structural or functional modifications, unsuitable or incorrect installations, environments not in keeping with the equipment's protection degree or with the required temperature and humidity conditions, failure to carry out maintenance and periodical inspections and poor repair work.

GENERAL SAFETY INFORMATION

Your attention is drawn to the following actions that could compromise the characteristics of the product:

- Read and retain the instructions which follow.
- Follow all indications and instructions given on the device.
- Make sure that the surface on which the device rests is stable. If it is not, the device could fall, seriously damaging it.
- Make sure that the device rests on a hard (non-padded) surface and that there is sufficient ventilation.
- Do not fix indissolubly the device or its accessories such as power supplies unless specifically provided in this manual.
- When positioning the device, make sure cables do not get damaged.
- [Only OEM equipment] The equipment must be installed in a kiosk or system that provides mechanical, electrical and fire protection.
- The mains power supply must comply with the rules in force in the Country where you intend to install the equipment.
- Make sure that there is an easily-accessible outlet with a capacity of no less than 10A closely to where the device is to be installed.
- Make sure the power cable provided with the appliance, or that you intend to use is suitable with the wall socket available in the system.
- Make sure the electrical system that supplies power to the device is equipped with a ground wire and is protected by a differential switch.
- Before any type of work is done on the machine, disconnect the power supply.
- Use the type of electrical power supply indicated on the device label.
- These devices are intended to be powered by a separately certified power module having an SELV, non-energy hazardous output. (IEC60950-1 second edition).
- [Only POS equipment] The energy to the equipment must be provided by power supply approved by CUSTOM S.p.A.
- Take care the operating temperature range of equipment and its ancillary components.
- Do not block the ventilation openings.
- Do not insert objects inside the device as this could cause short-circuiting or damage components that could jeopardize printer functioning.
- Do not carry out repairs on the device yourself, except for the normal maintenance operations given in the user manual.
- The equipment must be accessible on these components only to trained, authorized personnel.
- Periodically perform scheduled maintenance on the device to avoid dirt build-up that could compromise the correct, safe operation of the unit.
- Do not touch the head heating line with bare hands or metal objects. Do not perform any operation inside the printer immediately after printing because the head and motor tend to become very hot.
- Use consumables approved by CUSTOM S.p.A.



THE CE MARK AFFIXED TO THE PRODUCT CERTIFY THAT THE PRODUCT SATISFIES THE BASIC SAFETY REQUIREMENTS.

The device is in conformity with the essential Electromagnetic Compatibility and Electric Safety requirements laid down in Directives 2014/30/EU and 2014/35/EU inasmuch as it was designed in conformity with the provisions laid down in the following Standards:

- EN 55032 (*Electromagnetic compatibility of multimedia equipment - Emission Requirements*)
- EN 55024/EN55035 (*Electromagnetic compatibility of multimedia equipment - Immunity requirements*)
- EN IEC/EN62368-1 (*Audio/video, information and communication technology equipment*)

The device is in conformity with the essential requirements laid down in Directives 2014/53/EU about devices equipped with intentional radiators. The Declaration of Conformity and other available certifications can be downloaded from the site www.custom4u.it.



GUIDELINES FOR THE DISPOSAL OF THE PRODUCT

The crossed-out rubbish bin logo means that used electrical and electronic products shall NOT be mixed with unsorted municipal waste. For more detailed information about recycling of this product, refer to the instructions of your country for the disposal of these products.

- Do not dispose of this equipment as miscellaneous solid municipal waste, but arrange to have it collected separately.
- The re-use or correct recycling of the electronic and electrical equipment (EEE) is important in order to protect the environment and the wellbeing of humans.
- In accordance with European Directive WEEE 2012/19/EU, special collection points are available to which to deliver waste electrical and electronic equipment and the equipment can also be handed over to a distributor at the moment of purchasing a new equivalent type.
- The public administration and producers of electrical and electronic equipment are involved in facilitating the processes of the re-use and recovery of waste electrical and electronic equipment through the organisation of collection activities and the use of appropriate planning arrangements.
- Unauthorised disposal of waste electrical and electronic equipment is punishable by law with the appropriate penalties.



The format used for this manual improves use of natural resources reducing the quantity of necessary paper to print this copy.

INTRODUCTION



CUSTOM/POS EMULATION





INTRODUCTION

1 CONSULTING COMMANDS MANUAL 6



1 CONSULTING COMMANDS MANUAL

Each command reported in this manual is described as shown in the following picture. In the first heading field is reported the hexadecimal command value and the ASCII command value. In the second heading field reported the command function. In the third heading field are listed the devices on which it is possible to use the command (for example, device AAAA).

Link to index

Command value

Command function

Devices that use the command

0x0D
Print and carriage return

| | |
|-----------|------|
| Valid for | AAAA |
| | BBBB |
| | CCCC |

| | | |
|----------|-------|------|
| [Format] | Hex | 0x0D |
| | ASCII | CR |

[Range]

| | |
|---------------|--|
| [Description] | When Autofeed is "CR enabled", this command function in the same way as 0x0A, otherwise it is disregarded. |
|---------------|--|

| | |
|---------|---|
| [Notes] | This command sets the printing position to the beginning of the line. |
|---------|---|

Information valid for devices AAAA, BBBB, CCC

AAAA
BBBB

- This command sets the printing position to the beginning of the line.

Information valid only for devices AAAA, BBBB

CCCC

- This command is immediately executed even when the data buffer is full.
- This status is transmitted whenever data sequence is received.

Information valid only for device CCCC

| | |
|-------------|------|
| [Default] | |
| [Reference] | 0x0A |
| [Example] | |



The fields shown in the scheme of the previous figure have the following meaning:

| | |
|---------------|--|
| [Format] | hexadecimal and ASCII command value. |
| [Range] | Limits of the values the command and its variables can take. |
| [Description] | Description of command function. |
| [Notes] | Additional information about command use and settings. |
| [Default] | Default value of the command and its variables. |
| [Reference] | Pertaining commands related to described command. |
| [Example] | Example of using the command. |

Listed below are the meanings of some of symbols that may be found in the command description:

| | |
|---------------|--|
| 0x | indicates the representation of the command hexadecimal value (for example 0x40 means HEX 40). |
| n, m, t, x, y | are optional parameters that can have different values. |





CUSTOM/POS EMULATION

- 1 COMMANDS LISTED IN ALPHANUMERIC ORDER 10
- 2 COMMANDS LISTED BY FUNCTION 14



1 COMMANDS LISTED IN ALPHANUMERIC ORDER

| | | |
|----------------|-----------|-----|
| 0x08 | <BS> | 109 |
| 0x09 | <HT> | 110 |
| 0x0A | <LF> | 80 |
| 0x0D | <CR> | 81 |
| 0x10 0x04 | <DLE EOT> | 85 |
| 0x18 | <CAN> | 56 |
| 0x1B 0x20 | <ESC SP> | 57 |
| 0x1B 0x21 | <ESC !> | 58 |
| 0x1B 0x24 | <ESC \$> | 111 |
| 0x1B 0x25 | <ESC %> | 60 |
| 0x1B 0x26 | <ESC &> | 61 |
| 0x1B 0x28 0x76 | <ESC (v> | 112 |
| 0x1B 0x2A | <ESC *> | 99 |
| 0x1B 0x2D | <ESC -> | 62 |
| 0x1B 0x30 | <ESC 0> | 77 |
| 0x1B 0x32 | <ESC 2> | 78 |
| 0x1B 0x33 | <ESC 3> | 79 |
| 0x1B 0x34 | <ESC 4> | 63 |
| 0x1B 0x3D | <ESC => | 123 |
| 0x1B 0x3F | <ESC ?> | 64 |
| 0x1B 0x40 | <ESC @> | 124 |
| 0x1B 0x44 | <ESC D> | 113 |
| 0x1B 0x45 | <ESC E> | 65 |
| 0x1B 0x47 | <ESC G> | 66 |
| 0x1B 0x4A | <ESC J> | 82 |
| 0x1B 0x4D | <ESC M> | 67 |



| | | |
|-------------------------|-----------|-----|
| 0x1B 0x52 | <ESC R> | 68 |
| 0x1B 0x56 | <ESC V> | 69 |
| 0x1B 0x5C | <ESC \> | 115 |
| 0x1B 0x61 | <ESC a> | 116 |
| 0x1B 0x63 0x35 | <ESC c 5> | 125 |
| 0x1B 0x64 | <ESC d> | 83 |
| 0x1B 0x6D | <ESC m> | 121 |
| 0x1B 0x70 | <ESC p> | 126 |
| 0x1B 0x74 | <ESC t> | 70 |
| 0x1B 0x7B | <ESC {> | 72 |
| 0x1B 0xC1 | | 73 |
| 0x1C 0x25 | <FS %> | 74 |
| 0x1C 0x70 | <FS p> | 106 |
| 0x1C 0x71 | <FS q> | 108 |
| 0x1C 0xEA | | 91 |
| 0x1D 0x21 | <GS !> | 75 |
| 0x1D 0x28 0x6B | <GS (k> | 20 |
| 0x1D 0x28 0x6B [Fn 065] | <GS (k> | 22 |
| 0x1D 0x28 0x6B [Fn 066] | <GS (k> | 23 |
| 0x1D 0x28 0x6B [Fn 067] | <GS (k> | 24 |
| 0x1D 0x28 0x6B [Fn 068] | <GS (k> | 25 |
| 0x1D 0x28 0x6B [Fn 069] | <GS (k> | 26 |
| 0x1D 0x28 0x6B [Fn 080] | <GS (k> | 28 |
| 0x1D 0x28 0x6B [Fn 081] | <GS (k> | 29 |
| 0x1D 0x28 0x6B [Fn 165] | <GS (k> | 30 |
| 0x1D 0x28 0x6B [Fn 166] | <GS (k> | 31 |
| 0x1D 0x28 0x6B [Fn 167] | <GS (k> | 35 |
| 0x1D 0x28 0x6B [Fn 169] | <GS (k> | 36 |



| | | |
|-------------------------|-----------|-----|
| 0x1D 0x28 0x6B [Fn 180] | .<GS (k> | 37 |
| 0x1D 0x28 0x6B [Fn 181] | .<GS (k> | 38 |
| 0x1D 0x28 0x6B [Fn 182] | .<GS (k> | 39 |
| 0x1D 0x28 0x6B [Fn Q65] | .<GS (k> | 41 |
| 0x1D 0x28 0x6B [Fn Q66] | .<GS (k> | 42 |
| 0x1D 0x28 0x6B [Fn Q67] | .<GS (k> | 43 |
| 0x1D 0x28 0x6B [Fn Q68] | .<GS (k> | 44 |
| 0x1D 0x28 0x6B [Fn Q80] | .<GS (k> | 45 |
| 0x1D 0x28 0x6B [Fn Q81] | .<GS (k> | 46 |
| 0x1D 0x2A | .<GS *> | 101 |
| 0x1D 0x2F | .<GS /> | 103 |
| 0x1D 0x3A | .<GS :> | 119 |
| 0x1D 0x42 | .<GS B> | 76 |
| 0x1D 0x48 | .<GS H> | 47 |
| 0x1D 0x49 | .<GS l> | 127 |
| 0x1D 0x4C | .<GS L> | 117 |
| 0x1D 0x50 | .<GS P> | 128 |
| 0x1D 0x56 | .<GS V> | 122 |
| 0x1D 0x57 | .<GS W> | 118 |
| 0x1D 0x5E | .<GS ^> | 120 |
| 0x1D 0x66 | .<GS f> | 49 |
| 0x1D 0x68 | .<GS h> | 50 |
| 0x1D 0x6B | .<GS k> | 51 |
| 0x1D 0x72 | .<GS r> | 92 |
| 0x1D 0x76 0x30 | .<GS v 0> | 104 |
| 0x1D 0x77 | .<GS w> | 54 |
| 0x1D 0x7C | .<GS > | 84 |
| 0x1D 0xE0 | | 94 |



| | |
|-----------------|-----|
| 0x1D 0xE1 | 95 |
| 0x1D 0xE2 | 96 |
| 0x1D 0xE3 | 97 |
| 0x1D 0xE5 | 98 |
| 0x1D 0xE6 | 129 |
| 0x1D 0xE9 | 130 |
| 0x1D 0xF0 | 131 |



2 COMMANDS LISTED BY FUNCTION

COMMANDS FOR BARCODE PRINTING

| | |
|--|----|
| 0x1D 0x28 0x6B<GS (k> | 20 |
| Print two-dimensional barcode | |
| 0x1D 0x28 0x6B [Fn 065]<GS (k> | 22 |
| Specify the number of columns of PDF417 barcode | |
| 0x1D 0x28 0x6B [Fn 066]<GS (k> | 23 |
| Specify the number of rows of PDF417 barcode | |
| 0x1D 0x28 0x6B [Fn 067]<GS (k> | 24 |
| Specify the width of a module of PDF417 barcode | |
| 0x1D 0x28 0x6B [Fn 068]<GS (k> | 25 |
| Specify the height of a module of PDF417 barcode | |
| 0x1D 0x28 0x6B [Fn 069]<GS (k> | 26 |
| Specify the error correction level of PDF417 barcode | |
| 0x1D 0x28 0x6B [Fn 080]<GS (k> | 28 |
| Store the data in the barcode save area for printing in PDF417 format | |
| 0x1D 0x28 0x6B [Fn 081]<GS (k> | 29 |
| Encodes the data in the barcode save area and prints it in PDF417 format | |
| 0x1D 0x28 0x6B [Fn 165]<GS (k> | 30 |
| Specify encoding scheme of QRcode barcode | |
| 0x1D 0x28 0x6B [Fn 166]<GS (k> | 31 |
| Specify QRcode barcode version | |
| 0x1D 0x28 0x6B [Fn 167]<GS (k> | 35 |
| Specify dot size of the module of the QRcode barcode | |
| 0x1D 0x28 0x6B [Fn 169]<GS (k> | 36 |
| Specify the error correction level of the QRcode barcode | |
| 0x1D 0x28 0x6B [Fn 180]<GS (k> | 37 |
| Store the data in the barcode save area for printing in QRcode format | |
| 0x1D 0x28 0x6B [Fn 181]<GS (k> | 38 |
| Prints the data stored in the barcode save area in QRcode format | |
| 0x1D 0x28 0x6B [Fn 182]<GS (k> | 39 |
| Transmit the QRcode barcode size in the barcode save area | |
| 0x1D 0x28 0x6B [Fn Q65]<GS (k> | 41 |
| Specify the encoding scheme of DATAMATRIX barcode | |
| 0x1D 0x28 0x6B [Fn Q66]<GS (k> | 42 |
| Set rotation of DATAMATRIX barcode | |



| | | |
|--|-----------------------------|-----------|
| 0x1D 0x28 0x6B [Fn Q67] | <GS (k> | 43 |
| Set dot size of the module of DATAMATRIX barcode | | |
| 0x1D 0x28 0x6B [Fn Q68] | <GS (k> | 44 |
| Set size of DATAMATRIX barcode | | |
| 0x1D 0x28 0x6B [Fn Q80] | <GS (k> | 45 |
| Store the DATAMATRIX barcode data in the barcode save area | | |
| 0x1D 0x28 0x6B [Fn Q81] | <GS (k> | 46 |
| Encodes and prints the data stored in the barcode save area in DATAMATRIX format | | |
| 0x1D 0x48 | <GS H> | 47 |
| Select printing position of HRI characters in 1D barcodes | | |
| 0x1D 0x66 | <GS f> | 49 |
| Select font for HRI characters | | |
| 0x1D 0x68 | <GS h> | 50 |
| Set 1D barcode height | | |
| 0x1D 0x6B | <GS k> | 51 |
| Print 1D barcode | | |
| 0x1D 0x77 | <GS w> | 54 |
| Set 1D barcode width | | |

CHARACTER COMMANDS

| | | |
|---|--------------------------------|-----------|
| 0x18 | <CAN> | 56 |
| Cancel current line transmitted | | |
| 0x1B 0x20 | <ESC SP> | 57 |
| Set right-side character spacing | | |
| 0x1B 0x21 | <ESC !> | 58 |
| Select print modes | | |
| 0x1B 0x25 | <ESC %> | 60 |
| Enable or disable user-defined characters | | |
| 0x1B 0x26 | <ESC &> | 61 |
| Defines user-defined characters | | |
| 0x1B 0x2D | <ESC -> | 62 |
| Turn underline mode on or off | | |
| 0x1B 0x34 | <ESC 4> | 63 |
| Turn italic mode on or off | | |
| 0x1B 0x3F | <ESC ?> | 64 |
| Cancel user-defined characters | | |
| 0x1B 0x45 | <ESC E> | 65 |
| Turn bold mode on or off | | |



| | | |
|--|----------------------------|-----------|
| 0x1B 0x47 | <ESC G> | 66 |
| Turn double-strike mode on or off | | |
| 0x1B 0x4D | <ESC M> | 67 |
| Select character font | | |
| 0x1B 0x52 | <ESC R> | 68 |
| Select an international character set | | |
| 0x1B 0x56 | <ESC V> | 69 |
| Set 90° rotated print mode | | |
| 0x1B 0x74 | <ESC t> | 70 |
| Select character code table | | |
| 0x1B 0x7B | <ESC {> | 72 |
| Turn upside-down printing mode on or off | | |
| 0x1B 0xC1 | | 73 |
| Select character pitch | | |
| 0x1C 0x25 | <FS %> | 74 |
| Select the font type | | |
| 0x1D 0x21 | <GS !> | 75 |
| Select character size | | |
| 0x1D 0x42 | <GS B> | 76 |
| Turn black and white reverse printing mode on or off | | |

LINE SPACING COMMANDS

| | | |
|------------------------------|----------------------------|-----------|
| 0x1B 0x30 | <ESC 0> | 77 |
| Select 1/8-inch line spacing | | |
| 0x1B 0x32 | <ESC 2> | 78 |
| Select 1/6-inch line spacing | | |
| 0x1B 0x33 | <ESC 3> | 79 |
| Set line spacing | | |

PRINT COMMANDS

| | | |
|---------------------------|----------------------------|-----------|
| 0x0A | <LF> | 80 |
| Print and line feed | | |
| 0x0D | <CR> | 81 |
| Print and carriage return | | |
| 0x1B 0x4A | <ESC J> | 82 |
| Print and paper feed | | |



| | | |
|------------------------------|---------------|----|
| 0x1B 0x64 | <ESC d> | 83 |
| Print and feed paper n lines | | |
| 0x1D 0x7C | <GS > | 84 |
| Set printing density | | |

STATUS COMMANDS

| | | |
|--|-----------------|----|
| 0x10 0x04 | <DLE EOT> | 85 |
| Real-time status transmission | | |
| 0x1C 0xEA | | 91 |
| Transmit the device serial number | | |
| 0x1D 0x72 | <GS r> | 92 |
| Transmit status | | |
| 0x1D 0xE0 | | 94 |
| Enable or disable automatic FULL STATUS BACK | | |
| 0x1D 0xE1 | | 95 |
| Reading of length paper available before virtual paper-end | | |
| 0x1D 0xE2 | | 96 |
| Reading number of cuts performed by the autocutter | | |
| 0x1D 0xE3 | | 97 |
| Reading of length of printed paper | | |
| 0x1D 0xE5 | | 98 |
| Reading number of power up | | |

BIT-IMAGE COMMANDS

| | | |
|---------------------------|----------------|-----|
| 0x1B 0x2A | <ESC *> | 99 |
| Select bit image mode | | |
| 0x1D 0x2A | <GS *> | 101 |
| Define received bit image | | |
| 0x1D 0x2F | <GS /> | 103 |
| Print received bit image | | |
| 0x1D 0x76 0x30 | <GS v 0> | 104 |
| Print raster bit image | | |



LOGOS MANAGEMENT COMMANDS

| | | |
|------------------------|---------------------------|------------|
| 0x1C 0x70 | <FS p> | 106 |
| Print logo | | |
| 0x1C 0x71 | <FS q> | 108 |
| Logo storage | | |

PRINT POSITION COMMANDS

| | | |
|--------------------------------------|------------------------------|------------|
| 0x08 | <BS> | 109 |
| Back space | | |
| 0x09 | <HT> | 110 |
| Horizontal tab | | |
| 0x1B 0x24 | <ESC \$> | 111 |
| Set absolute print position | | |
| 0x1B 0x28 0x76 | <ESC (v> | 112 |
| Set relative vertical print position | | |
| 0x1B 0x44 | <ESC D> | 113 |
| Set horizontal tab positions | | |
| 0x1B 0x5C | <ESC \> | 115 |
| Set relative print position | | |
| 0x1B 0x61 | <ESC a> | 116 |
| Select justification | | |
| 0x1D 0x4C | <GS L> | 117 |
| Set left margin | | |
| 0x1D 0x57 | <GS W> | 118 |
| Set printing area width | | |

MACRO FUNCTIONS CONTROL

| | | |
|----------------------------------|---------------------------|------------|
| 0x1D 0x3A | <GS :> | 119 |
| Start or end of macro definition | | |
| 0x1D 0x5E | <GS ^> | 120 |
| Execute macro | | |



COMMANDS FOR MECHANISM CONTROL

| | | |
|------------------------|----------------------------|------------|
| 0x1B 0x6D | <ESC m> | 121 |
| Partial cut | | |
| 0x1D 0x56 | <GS V> | 122 |
| Select cut mode | | |

MISCELLANEOUS COMMANDS

| | | |
|--|------------------------------|------------|
| 0x1B 0x3D | <ESC => | 123 |
| Select peripheral device | | |
| 0x1B 0x40 | <ESC @> | 124 |
| Initialize device | | |
| 0x1B 0x63 0x35 | <ESC c 5> | 125 |
| Enable or disable keys panel | | |
| 0x1B 0x70 | <ESC p> | 126 |
| Generate pulse on drawer connector | | |
| 0x1D 0x49 | <GS I> | 127 |
| Transmit device ID | | |
| 0x1D 0x50 | <GS P> | 128 |
| Set horizontal and vertical motion units | | |
| 0x1D 0xE6 | | 129 |
| Virtual paper end limit | | |
| 0x1D 0xE9 | | 130 |
| Set minimum ticket length | | |
| 0x1D 0xF0 | | 131 |
| Set print mode | | |



COMMANDS FOR BARCODE PRINTING

0x1D 0x28 0x6B

<GS (k>

Print two-dimensional barcode

| | | | | | | | | |
|---------------|---|------|--------------|--|----|----|----|----|
| Valid for | P3 | | | | | | | |
| [Format] | Hex | 1D | 28 | 6B | pL | pH | cn | fn |
| | ASCII | GS | (| k | pL | pH | cn | fn |
| [Range] | cn = 0x30, 0x31, 0x51 0x41 ≤ fn ≤ 0x45, 0x50 ≤ fn ≤ 0x52 | | | | | | | |
| [Description] | Processes the data concerning two-dimensional barcode. <ul style="list-style-type: none"> Barcode type is specified by cn Function is specified by fn | | | | | | | |
| | cn | fn | FUNCTION | | | | | |
| | 0x30 | 0x41 | Function 065 | PDF417: Specify the number of columns | | | | |
| | 0x30 | 0x42 | Function 066 | PDF417: Specify the number of rows | | | | |
| | 0x30 | 0x43 | Function 067 | PDF417: Specify the width of module | | | | |
| | 0x30 | 0x44 | Function 068 | PDF417: Specify the module height | | | | |
| | 0x30 | 0x45 | Function 069 | PDF417: Specify the error correction level | | | | |
| | 0x30 | 0x50 | Function 080 | PDF417: Store the received data in the barcode save area | | | | |
| | 0x30 | 0x51 | Function 081 | PDF417: Print the barcode data in the barcode save area | | | | |
| | 0x31 | 0x41 | Function 165 | QRcode: Specify encoding scheme | | | | |
| | 0x31 | 0x42 | Function 166 | QRcode: Specify the selected version | | | | |
| | 0x31 | 0x43 | Function 167 | QRcode: Specify size of barcode | | | | |
| | 0x31 | 0x45 | Function 169 | QRcode: Specify the error correction level | | | | |
| | 0x31 | 0x50 | Function 180 | QRcode: Store the received data in the barcode save area | | | | |
| | 0x31 | 0x51 | Function 181 | QRcode: Print the barcode data | | | | |
| | 0x31 | 0x52 | Function 182 | QRcode: Transmit the barcode size in the barcode save area | | | | |



| | | | |
|------|------|------------------------------|--|
| 0x51 | 0x41 | Function Q65 | DATAMATRIX: Set encoding scheme |
| 0x51 | 0x42 | Function Q66 | DATAMATRIX: Set rotate |
| 0x51 | 0x43 | Function Q67 | DATAMATRIX: Set dot size of the module |
| 0x51 | 0x44 | Function Q68 | DATAMATRIX: Set size of barcode |
| 0x51 | 0x50 | Function Q80 | DATAMATRIX: Store the received data in the barcode save area |
| 0x51 | 0x51 | Function Q81 | DATAMATRIX: Print the barcode data in the barcode save area |

[Notes]

[Default]

[Reference]

[Example]




0x1D 0x28 0x6B [Fn 065]

<GS (k>

Specify the number of columns of PDF417 barcode

| Valid for | P3 | | | | | | | | |
|---------------|---|----|----|----|----|----|----|----|---|
| [Format] | Hex | 1D | 28 | 6B | pL | pH | 30 | 41 | n |
| | ASCII | GS | (| k | pL | pH | 0 | A | n |
| [Range] | (pL + pH × 256) = 3 (pL = 0x03, pH = 0x00) 0x00 ≤ n ≤ 0x1E | | | | | | | | |
| [Description] | Specifies the number of columns of PDF417 barcode. <ul style="list-style-type: none">• pL and pH specify the number of successive bytes to be sent.• n = 0x00 specifies auto processing. When auto processing is specified, the maximum number of columns in the data area is 30 columns.• When n is not 0x00, specifies the number of columns of the data area as n code word. | | | | | | | | |
| [Notes] | <ul style="list-style-type: none">• The following data is not included in the number of columns:<ul style="list-style-type: none">- start pattern and stop pattern- indicator code word of left and right• Settings are effective until 0x1B 0x40 is executed or the device is reset or turned off. | | | | | | | | |
| [Default] | n = 0x00 | | | | | | | | |
| [Reference] | 0x1D 0x28 0x6B | | | | | | | | |
| [Example] | To define 3 columns, the command sequence is: 0x1D 0x28 0x6B 0x03 0x00 0x30 0x41 0x03 | | | | | | | | |






0x1D 0x28 0x6B [Fn 066]

<GS (k>

Specify the number of rows of PDF417 barcode

| | | | | | | | | | |
|---------------|--|----|----|----|----|----|----|----|---|
| Valid for | P3 | | | | | | | | |
| [Format] | Hex | 1D | 28 | 6B | pL | pH | 30 | 42 | n |
| | ASCII | GS | (| k | pL | pH | 0 | B | n |
| [Range] | (pL + pH × 256) = 3 (pL = 0x03, pH = 0x00) n = 0x00 0x03 ≤ n ≤ 0x14 | | | | | | | | |
| [Description] | Specifies the number of rows of PDF417 barcode. <ul style="list-style-type: none">• pL and pH specify the number of successive bytes to be sent.• n = 0x00 specifies auto processing. When auto processing is specified, the maximum number of rows is 20.• When n is not 0x00, specifies the number of rows of the data area as n rows. | | | | | | | | |
| [Notes] | Settings are effective until 0x1B 0x40 is executed or the device is reset or turned off. | | | | | | | | |
| [Default] | n = 0x00 | | | | | | | | |
| [Reference] | 0x1D 0x28 0x6B | | | | | | | | |
| [Example] | To define 6 rows, the command sequence is: 0x1D 0x28 0x6B 0x03 0x00 0x30 0x42 0x06 | | | | | | | | |






0x1D 0x28 0x6B [Fn 067]

<GS (k>

Specify the width of a module of PDF417 barcode

| | | | | | | | | | |
|---------------|--|----|----|----|----|----|----|----|---|
| Valid for | P3 | | | | | | | | |
| [Format] | Hex | 1D | 28 | 6B | pL | pH | 30 | 43 | n |
| | ASCII | GS | (| k | pL | pH | 0 | C | n |
| [Range] | (pL + pH × 256) = 3 (pL = 0x03, pH = 0x00) 0x02 ≤ n ≤ 0x08 | | | | | | | | |
| [Description] | Specifies the width of a module of PDF417 barcode. • pL and pH specify the number of successive bytes to be sent. | | | | | | | | |
| [Notes] | Settings are effective until 0x1B 0x40 is executed or the device is reset or turned off. | | | | | | | | |
| [Default] | n = 0x03 | | | | | | | | |
| [Reference] | 0x1D 0x28 0x6B | | | | | | | | |
| [Example] | To set width = 4, the command sequence is: 0x1D 0x28 0x6B 0x03 0x00 0x30 0x43 0x04 | | | | | | | | |






0x1D 0x28 0x6B [Fn 068]

<GS (k>

Specify the height of a module of PDF417 barcode

| | | | | | | | | | |
|---------------|---|----|----|----|----|----|----|----|---|
| Valid for | P3 | | | | | | | | |
| [Format] | Hex | 1D | 28 | 6B | pL | pH | 30 | 44 | n |
| | ASCII | GS | (| k | pL | pH | 0 | D | n |
| [Range] | $(pL + pH \times 256) = 3$ (pL = 0x03, pH = 0x00) $0x02 \leq n \leq 0x08$ | | | | | | | | |
| [Description] | Specifies the height of the module of the PDF417 barcode. • pL and pH specify the number of successive bytes to be sent. | | | | | | | | |
| [Notes] | Settings are effective until 0x1B 0x40 is executed or the device is reset or turned off. | | | | | | | | |
| [Default] | n = 0x03 | | | | | | | | |
| [Reference] | 0x1D 0x28 0x6B | | | | | | | | |
| [Example] | To set height = 4, the command sequence is: 0x1D 0x28 0x6B 0x03 0x00 0x30 0x44 0x04 | | | | | | | | |





0x1D 0x28 0x6B [Fn 069]

<GS (k>

Specify the error correction level of PDF417 barcode

| | | | | | | | | | | |
|---------------|--|----|----|----|----|----|----|----|---|---|
| Valid for | P3 | | | | | | | | | |
| [Format] | Hex | 1D | 28 | 6B | pL | pH | 30 | 45 | m | n |
| | ASCII | GS | (| k | pL | pH | 0 | E | m | n |
| [Range] | <p>(pL + pH × 256) = 4 (pL = 0x04, pH = 0x00)</p> <p>m = 0x30 0x30 ≤ n ≤ 0x38</p> <p>m = 0x31 0x01 ≤ n ≤ 0x28</p> | | | | | | | | | |
| [Description] | <p>Specifies the error correction level of PDF417 barcode. This error correction allows the barcode to endure some damage without causing loss of data. The error correction level depends on the amount of data that needs to be encoded, the size and the amount of symbol damage that could occur.</p> <ul style="list-style-type: none"> • pL and pH specify the number of successive bytes to be sent. • The error correction level is specified by “level” when m = 0x30. • The error correction level is specified by “ratio” when m = 0x31 [n × 10%]. | | | | | | | | | |
| [Notes] | <ul style="list-style-type: none"> • Error correction level is specified by either “level” or “ratio”. • Error correction level specified by “level” (m = 0x30) is as follows. The number of the error correction code word is fixed regardless of the number of code words on the data area. | | | | | | | | | |

| n | CORRECTION LEVEL | N. OF ERROR CORRECTION CODE WORD |
|------|--------------------------|----------------------------------|
| 0x30 | Error correction level 0 | 2 |
| 0x31 | Error correction level 1 | 4 |
| 0x32 | Error correction level 2 | 8 |
| 0x33 | Error correction level 3 | 16 |
| 0x34 | Error correction level 4 | 32 |
| 0x35 | Error correction level 5 | 64 |
| 0x36 | Error correction level 6 | 128 |
| 0x37 | Error correction level 7 | 256 |
| 0x38 | Error correction level 8 | 512 |



- Error correction level specified by “ratio” (m = 0x31) is as follows. The error correction level is defined by the calculated value [number of data code word × n × 0.1 = (A)]. The number of the error correction code word is changeable in proportion to the number of the code words on the data area.

| CALCULATED VALUE (A) | CORRECTION LEVEL | N. OF ERROR CORRECTION CODE WORD |
|-------------------------|--------------------------|-------------------------------------|
| 0 - 3 | Error correction level 1 | 4 |
| 4 - 10 | Error correction level 2 | 8 |
| 11 - 20 | Error correction level 3 | 16 |
| 21 - 45 | Error correction level 4 | 32 |
| 46 - 100 | Error correction level 5 | 64 |
| 101 - 200 | Error correction level 6 | 128 |
| 201 - 400 | Error correction level 7 | 256 |
| > 400 | Error correction level 8 | 512 |

- Settings are effective until 0x1B 0x40 is executed or the device is reset or turned off.

[Default]

m = 0x31, n = 0x01 [ratio: 10%]

[Reference]

0x1D 0x28 0x6B

[Example]

To set error correction = 0.2, the command sequence is:
0x1D 0x28 0x6B 0x03 0x00 0x30 0x45 0x30 0x02



0x1D 0x28 0x6B [Fn 080]

<GS (k>

Store the data in the barcode save area for printing in PDF417 format

| | | | | | | | | | | |
|----------------|---|----|----|----|----|----|----|----|----|---------|
| Valid for | P3 | | | | | | | | | |
| [Format] | Hex | 1D | 28 | 6B | pL | pH | 30 | 50 | 30 | d1...dk |
| | ASCII | GS | (| k | pL | pH | 0 | P | 0 | d1...dk |
| [Range] | <p>$0x00 \leq d \leq 0xFF$ $k = (pL + pH \times 256) - 3$</p> <ul style="list-style-type: none">• PDF417 barcode only with ASCII characters: $4 \leq (pL + pH \times 256) \leq 1112$ ($0x00 \leq pL \leq 0xFF$, $0x00 \leq pH \leq 0x04$)• PDF417 barcode only with alphanumeric characters: $4 \leq (pL + pH \times 256) \leq 1854$ ($0x00 \leq pL \leq 0xFF$, $0x00 \leq pH \leq 0x07$)• PDF417 barcode only with numeric characters: $4 \leq (pL + pH \times 256) \leq 2729$ ($0x00 \leq pL \leq 0xFF$, $0x00 \leq pH \leq 0x0A$) | | | | | | | | | |
| [Description] | <p>Stores the data (d1...dk) in the barcode save area for printing in PDF417 format.</p> <ul style="list-style-type: none">• pL and pH specify the number of successive bytes to be sent.• k bytes of d1...dk are processed as barcode data. | | | | | | | | | |
| [Notes][Notes] | <ul style="list-style-type: none">• Data stored in the barcode save area by this function are processed by Function 081 and then reserved.• Specify only the data code word of the barcode with this function. Be sure not to include the control data in the data d1...dk because they are added automatically by the device.• Settings are effective until 0x1B 0x40 is executed or the device is reset or turned off. | | | | | | | | | |
| [Default] | | | | | | | | | | |
| [Reference] | 0x1D 0x28 0x6B | | | | | | | | | |
| [Example] | | | | | | | | | | |



0x1D 0x28 0x6B [Fn 081]

<GS (k>

Encodes the data in the barcode save area and prints it in PDF417 format

| | | | | | | | | | |
|---------------|---|----|----|----|----|----|----|----|----|
| Valid for | P3 | | | | | | | | |
| [Format] | Hex | 1D | 28 | 6B | pL | pH | 30 | 51 | 30 |
| | ASCII | GS | (| k | pL | pH | 0 | Q | 0 |
| [Range] | (pL + pH × 256) = 3 (pL = 0x03, pH = 0x00) | | | | | | | | |
| [Description] | <p>Encodes the data in the barcode save area and prints it in PDF417 format.</p> <ul style="list-style-type: none"> • pL and pH specify the number of successive bytes to be sent. | | | | | | | | |
| [Notes] | <ul style="list-style-type: none"> • In standard mode, use this function when device is at the beginning of a line or there is no data in the print buffer. • A barcode that size exceeds the printing area cannot be printed. • If there is any error described below in the data of the barcode save area, it cannot be printed. <ul style="list-style-type: none"> - There is no data (Function 080 is not processed). - If [(number of columns × number of rows) < number of code word] when auto processing is specified for number of columns and number of rows. - Number of code word exceeds 928 in the data area. • When auto processing (Function 065) is specified, the number of columns is calculated by the current printing area, module width (Function 067) and the code word in the data area. Maximum number of the columns is 30. | | | | | | | | |
| [Default] | | | | | | | | | |
| [Reference] | 0x1D 0x28 0x6B | | | | | | | | |
| [Example] | <p>To print the PDF417 barcode data the command sequence is:</p> <p>0x1D 0x28 0x6B 0x03 0x00 0x30 0x51 0x30</p> | | | | | | | | |



0x1D 0x28 0x6B [Fn 165]

<GS (k>

Specify encoding scheme of QRcode barcode

| Valid for | P3 | | | | | | | | | | | | | | | |
|---------------|--|----|----|----|----|----|----|----|----|----|----|-----------------|------|----------------|------|---------|
| [Format] | Hex | 1D | 28 | 6B | pL | pH | 31 | 41 | n1 | n2 | | | | | | |
| | ASCII | GS | (| k | pL | pH | 1 | A | n1 | n2 | | | | | | |
| [Range] | (pL+pH × 256) = 4 (pL = 0x04, pH = 0x00) 0x32 ≤ n1 ≤ 0x33 n2 = 0x00 | | | | | | | | | | | | | | | |
| [Description] | Specifies encoding type of QRcode barcode, based on the value of n1 as follows: | | | | | | | | | | | | | | | |
| | <table><tr><th>n1</th><th>ENCODING SCHEME</th></tr><tr><td>0x32</td><td>QRcode model 2</td></tr><tr><td>0x33</td><td>MicroQR</td></tr></table> | | | | | | | | | | n1 | ENCODING SCHEME | 0x32 | QRcode model 2 | 0x33 | MicroQR |
| n1 | ENCODING SCHEME | | | | | | | | | | | | | | | |
| 0x32 | QRcode model 2 | | | | | | | | | | | | | | | |
| 0x33 | MicroQR | | | | | | | | | | | | | | | |
| [Notes] | <ul style="list-style-type: none">• QRcode: Encode all extended ASCII characters data up to a maximum length of 7089 numeric digits, 4296 alphabetic characters or 2953 bytes of data.• pL and pH specify the number of successive bytes to be sent.• MicroQR (a miniature version of the QRcode barcode for short message): Encode all numbers from 0 to 9 up to a maximum length of 35 characters. | | | | | | | | | | | | | | | |
| [Default] | n1 =0x32, n2 = 0x00 | | | | | | | | | | | | | | | |
| [Reference] | 0x1D 0x28 0x6B | | | | | | | | | | | | | | | |

[Example]



QRcode Model 2



MicroQR



0x1D 0x28 0x6B [Fn 166]

<GS (k>

Specify QRcode barcode version

| | | | | | | | | | |
|---------------|--|----|----|----|----|----|----|----|---|
| Valid for | P3 | | | | | | | | |
| [Format] | Hex | 1D | 28 | 6B | pL | pH | 31 | 42 | n |
| | ASCII | GS | (| k | pL | pH | 1 | B | n |
| [Range] | (pL + pH × 256) = 3 (pL = 0x03, pH = 0x00) 0x00 ≤ n ≤ 0x28 | | | | | | | | |
| [Description] | Defines QRcode version to be printed. | | | | | | | | |
| [Notes] | <ul style="list-style-type: none"> • If selected version has not enough capacity to store the saved amount of data, next smallest version capable of that capacity will be printed. • For QRcode version capacity according to ECC (Error Correction Capability) and data type refer to following table. • With n = 0x00 the selection of the version occurs automatically according to the one that allows the printing of the requested data. | | | | | | | | |

| n | VERSION | MODULES | ECC LEVEL | NUMERIC | ALPHANUMERIC | BINARY |
|------|---------|---------|-----------|---------|--------------|--------|
| 0x00 | AUTO | - | - | - | - | - |
| 0x01 | 1 | 21 x 21 | L | 40 | 24 | 16 |
| | | | M | 33 | 19 | 13 |
| | | | Q | 26 | 15 | 10 |
| | | | H | 16 | 9 | 6 |
| 0x02 | 2 | 25 x 25 | L | 76 | 46 | 31 |
| | | | M | 62 | 37 | 25 |
| | | | Q | 47 | 28 | 19 |
| | | | H | 33 | 19 | 13 |
| 0x03 | 3 | 29 x 29 | L | 126 | 76 | 52 |
| | | | M | 100 | 60 | 41 |
| | | | Q | 76 | 46 | 31 |
| | | | H | 57 | 34 | 23 |
| 0x04 | 4 | 33 x 33 | L | 186 | 113 | 77 |
| | | | M | 148 | 89 | 61 |
| | | | Q | 110 | 66 | 45 |
| | | | H | 81 | 49 | 33 |
| 0x05 | 5 | 37 x 37 | L | 254 | 153 | 105 |
| | | | M | 201 | 121 | 83 |
| | | | Q | 143 | 86 | 59 |
| | | | H | 105 | 63 | 43 |
| 0x06 | 6 | 41 x 41 | L | 321 | 194 | 133 |
| | | | M | 254 | 153 | 105 |
| | | | Q | 177 | 107 | 73 |
| | | | H | 138 | 83 | 57 |
| 0x07 | 7 | 45 x 45 | L | 369 | 223 | 153 |
| | | | M | 292 | 177 | 121 |
| | | | Q | 206 | 124 | 85 |
| | | | H | 153 | 92 | 63 |



| n | VERSION | MODULES | ECC LEVEL | NUMERIC | ALPHANUMERIC | BINARY |
|------|---------|---------|-----------|---------|--------------|--------|
| 0x08 | 8 | 49 x 49 | L | 460 | 278 | 191 |
| | | | M | 364 | 220 | 151 |
| | | | Q | 258 | 156 | 107 |
| | | | H | 201 | 121 | 83 |
| 0x09 | 9 | 53 x 53 | L | 551 | 334 | 229 |
| | | | M | 431 | 261 | 179 |
| | | | Q | 311 | 188 | 129 |
| | | | H | 234 | 142 | 97 |
| 0x0A | 10 | 57 x 57 | L | 651 | 394 | 270 |
| | | | M | 512 | 310 | 212 |
| | | | Q | 363 | 220 | 150 |
| | | | H | 287 | 173 | 118 |
| 0x0B | 11 | 61 x 61 | L | 771 | 467 | 320 |
| | | | M | 603 | 365 | 250 |
| | | | Q | 426 | 258 | 176 |
| | | | H | 330 | 199 | 136 |
| 0x0C | 12 | 65 x 65 | L | 882 | 534 | 366 |
| | | | M | 690 | 418 | 286 |
| | | | Q | 488 | 295 | 202 |
| | | | H | 373 | 226 | 154 |
| 0x0D | 13 | 69 x 69 | L | 1021 | 618 | 424 |
| | | | M | 795 | 482 | 330 |
| | | | Q | 579 | 351 | 240 |
| | | | H | 426 | 258 | 176 |
| 0x0E | 14 | 73 x 73 | L | 1100 | 666 | 457 |
| | | | M | 870 | 527 | 361 |
| | | | Q | 620 | 375 | 257 |
| | | | H | 467 | 282 | 193 |
| 0x0F | 15 | 77 x 77 | L | 1249 | 757 | 519 |
| | | | M | 990 | 599 | 411 |
| | | | Q | 702 | 425 | 291 |
| | | | H | 529 | 320 | 219 |
| 0x10 | 16 | 81 x 81 | L | 1407 | 853 | 585 |
| | | | M | 1081 | 655 | 449 |
| | | | Q | 774 | 469 | 321 |
| | | | H | 601 | 364 | 249 |
| 0x11 | 17 | 85 x 85 | L | 1547 | 937 | 643 |
| | | | M | 1211 | 733 | 503 |
| | | | Q | 875 | 530 | 363 |
| | | | H | 673 | 407 | 279 |
| 0x12 | 18 | 89 x 89 | L | 1724 | 1045 | 717 |
| | | | M | 1345 | 815 | 559 |
| | | | Q | 947 | 573 | 393 |
| | | | H | 745 | 451 | 309 |
| 0x13 | 19 | 93 x 93 | L | 1902 | 1152 | 791 |
| | | | M | 1499 | 908 | 623 |
| | | | Q | 1062 | 643 | 441 |
| | | | H | 812 | 492 | 337 |
| 0x14 | 20 | 97 x 97 | L | 2060 | 1248 | 857 |
| | | | M | 1599 | 969 | 665 |
| | | | Q | 1158 | 701 | 481 |
| | | | H | 918 | 556 | 381 |



| n | VERSION | MODULES | ECC LEVEL | NUMERIC | ALPHANUMERIC | BINARY |
|------|---------|-----------|-----------|---------|--------------|--------|
| 0x15 | 21 | 101 x 101 | L | 2231 | 1351 | 928 |
| | | | M | 1707 | 1034 | 710 |
| | | | Q | 1223 | 741 | 508 |
| | | | H | 968 | 586 | 402 |
| 0x16 | 22 | 105 x 105 | L | 2408 | 1459 | 1002 |
| | | | M | 1871 | 1133 | 778 |
| | | | Q | 1357 | 822 | 564 |
| | | | H | 1055 | 639 | 438 |
| 0x17 | 23 | 109 x 109 | L | 2619 | 1587 | 1090 |
| | | | M | 2058 | 1247 | 856 |
| | | | Q | 1467 | 889 | 610 |
| | | | H | 1107 | 671 | 460 |
| 0x18 | 24 | 113 x 113 | L | 2811 | 1703 | 1170 |
| | | | M | 2187 | 1325 | 90 |
| | | | Q | 1587 | 92 | 60 |
| | | | H | 1227 | 73 | 50 |
| 0x19 | 25 | 117 x 117 | L | 3056 | 1852 | 1272 |
| | | | M | 2394 | 1450 | 96 |
| | | | Q | 1717 | 1040 | 74 |
| | | | H | 1285 | 78 | 54 |
| 0x1A | 26 | 121 x 121 | L | 3282 | 198 | 1366 |
| | | | M | 2543 | 1541 | 1058 |
| | | | Q | 1803 | 1093 | 70 |
| | | | H | 1424 | 83 | 52 |
| 0x1B | 27 | 125 x 125 | L | 3516 | 2131 | 1464 |
| | | | M | 2700 | 1636 | 1124 |
| | | | Q | 1932 | 1171 | 84 |
| | | | H | 1500 | 89 | 64 |
| 0x1C | 28 | 129 x 129 | L | 3668 | 2222 | 1527 |
| | | | M | 2856 | 1731 | 118 |
| | | | Q | 2084 | 1262 | 87 |
| | | | H | 1580 | 97 | 67 |
| 0x1D | 29 | 133 x 133 | L | 3908 | 2368 | 1627 |
| | | | M | 3034 | 1838 | 1263 |
| | | | Q | 2180 | 1321 | 97 |
| | | | H | 1676 | 1015 | 67 |
| 0x1E | 30 | 137 x 137 | L | 4157 | 251 | 1731 |
| | | | M | 3288 | 1993 | 136 |
| | | | Q | 2357 | 1428 | 91 |
| | | | H | 1781 | 107 | 71 |
| 0x1F | 31 | 141 x 141 | L | 4416 | 2676 | 183 |
| | | | M | 3485 | 2112 | 1451 |
| | | | Q | 2472 | 1498 | 102 |
| | | | H | 1896 | 114 | 69 |
| 0x20 | 32 | 145 x 145 | L | 4685 | 283 | 1951 |
| | | | M | 3692 | 2237 | 1537 |
| | | | Q | 266 | 1617 | 1111 |
| | | | H | 2021 | 1225 | 81 |
| 0x21 | 33 | 149 x 149 | L | 4964 | 3008 | 2067 |
| | | | M | 3908 | 2368 | 1627 |
| | | | Q | 2804 | 16 | 1167 |
| | | | H | 2156 | 1306 | 87 |



| n | VERSION | MODULES | ECC LEVEL | NUMERIC | ALPHANUMERIC | BINARY |
|------|---------|-----------|-----------|---------|--------------|--------|
| 0x22 | 34 | 153 x 153 | L | 5252 | 3182 | 2187 |
| | | | M | 4133 | 2505 | 1721 |
| | | | Q | 2948 | 1786 | 1227 |
| | | | H | 2300 | 1393 | 97 |
| 0x23 | 35 | 157 x 157 | L | 5528 | 3350 | 2302 |
| | | | M | 4342 | 2631 | 1808 |
| | | | Q | 3080 | 1866 | 1282 |
| | | | H | 2360 | 1430 | 92 |
| 0x24 | 36 | 161 x 161 | L | 5835 | 3536 | 2430 |
| | | | M | 4587 | 277 | 1910 |
| | | | Q | 3243 | 1965 | 1350 |
| | | | H | 2523 | 152 | 1050 |
| 0x25 | 37 | 165 x 165 | L | 6152 | 3728 | 2562 |
| | | | M | 4774 | 2893 | 1988 |
| | | | Q | 3416 | 2070 | 1422 |
| | | | H | 2624 | 1590 | 1092 |
| 0x26 | 38 | 169 x 169 | L | 6478 | 3926 | 2698 |
| | | | M | 5038 | 3053 | 2098 |
| | | | Q | 3598 | 2180 | 1498 |
| | | | H | 2734 | 1657 | 1138 |
| 0x27 | 39 | 173 x 173 | L | 6742 | 4086 | 2808 |
| | | | M | 5312 | 321 | 2212 |
| | | | Q | 3790 | 2297 | 1578 |
| | | | H | 2926 | 1773 | 1218 |
| 0x28 | 40 | 177 x 177 | L | 7088 | 4295 | 2952 |
| | | | M | 5595 | 3390 | 2330 |
| | | | Q | 3992 | 241 | 1662 |
| | | | H | 3056 | 1851 | 1272 |

[Default] n = 0x00

[Reference] 0x1D 0x28 0x6B


[Example] To select QRcode version 8 the command sequence is:
0x1D 0x28 0x6B 0x03 0x00 0x31 0x42 0x08



0x1D 0x28 0x6B [Fn 167]

<GS (k>

Specify dot size of the module of the QRcode barcode

| | | | | | | | | | |
|---------------|--|----|----|----|----|----|----|----|---|
| Valid for | P3 | | | | | | | | |
| [Format] | Hex | 1D | 28 | 6B | pL | pH | 31 | 43 | n |
| | ASCII | GS | (| k | pL | pH | 1 | C | n |
| [Range] | (pL + pH × 256) = 3 (pL = 0x03, pH = 0x00) 0x02 ≤ n ≤ 0x18 | | | | | | | | |
| [Description] | Specifies numbers of dots for each pixel of QRcode barcode. | | | | | | | | |
| [Notes] | pL and pH specify the number of successive bytes to be sent. | | | | | | | | |
| [Default] | n = 0x06 | | | | | | | | |
| [Reference] | 0x1D 0x28 0x6B | | | | | | | | |
| [Example] |  | | | | | | | | |



0x1D 0x28 0x6B [Fn 169]

<GS (k>

Specify the error correction level of the QRcode barcode

| | | | | | | | | | |
|---------------|--|----|----|----|----|----|----|----|---|
| Valid for | P3 | | | | | | | | |
| [Format] | Hex | 1D | 28 | 6B | pL | pH | 31 | 45 | n |
| | ASCII | GS | (| k | pL | pH | 1 | E | n |
| [Range] | (pL + pH × 256) = 3 (pL = 0x03, pH = 0x00) 0x30 ≤ n ≤ 0x34 | | | | | | | | |
| [Description] | Specifies the ECC level (Error Correction Capability) of QRcode barcode. | | | | | | | | |

| n | | ECC level | |
|------|------------------------------|----------------------------------|--|
| 0x30 | | AUTO | |
| 0x31 | ECC L = approx 20% of symbol | Recovery Capability = approx 7% | |
| 0x32 | ECC M = approx 37% of symbol | Recovery Capability = approx 15% | |
| 0x33 | ECC Q = approx 55% of symbol | Recovery Capability = approx 25% | |
| 0x34 | ECC H = approx 65% of symbol | Recovery Capability = approx 30% | |

[Notes] pL and pH specify the number of successive bytes to be sent.

[Default] n = 0x30

[Reference] [0x1D 0x28 0x6B](#)

[Example]

Level L



Level M



Level Q



Level H



Recover Capability

L

M

Q

H

7%

15%

25%

30%



0x1D 0x28 0x6B [Fn 180]

<GS (k>

Store the data in the barcode save area for printing in QRcode format

| | | | | | | | | | | |
|---------------|--|----|----|----|----|----|----|----|----|---------|
| Valid for | P3 | | | | | | | | | |
| [Format] | Hex | 1D | 28 | 6B | pL | pH | 31 | 50 | 31 | d1...dk |
| | ASCII | GS | (| k | pL | pH | 1 | P | 1 | d1...dk |
| [Range] | <p>$0x00 \leq d \leq 0xFF$ $k = (pL + pH \times 256) - 3$</p> <ul style="list-style-type: none"> QRcode barcode only with binary characters (8 bit): $4 \leq (pL + pH \times 256) \leq 2957$ ($0x00 \leq pL \leq 0xFF$, $0x00 \leq pH \leq 0x0B$) QRcode barcode only with alphanumeric characters: $4 \leq (pL + pH \times 256) \leq 4300$ ($0x00 \leq pL \leq 0xFF$, $0x00 \leq pH \leq 0x10$) QRcode barcode only with numeric characters: $4 \leq (pL + pH \times 256) \leq 7093$ ($0x00 \leq pL \leq 0xFF$, $0x00 \leq pH \leq 0x1B$) | | | | | | | | | |
| [Description] | Store the data (d1...dk) in the barcode save area for printing in QRcode format. | | | | | | | | | |
| [Notes] | <ul style="list-style-type: none"> Data stored in the barcode save area by this function are processed by Function 181 and then reserved. pL and pH specify the number of successive bytes to be sent. k bytes of d1...dk are processed as barcode data. Specify only the data code word of the barcode with this function. | | | | | | | | | |
| [Default] | | | | | | | | | | |
| [Reference] | 0x1D 0x28 0x6B | | | | | | | | | |
| [Example] | | | | | | | | | | |



0x1D 0x28 0x6B [Fn 181]

<GS (k>

Prints the data stored in the barcode save area in QRcode format

| | | | | | | | | | |
|---------------|---|----|----|----|----|----|----|----|----|
| Valid for | P3 | | | | | | | | |
| [Format] | Hex | 1D | 28 | 6B | pL | pH | 31 | 51 | 31 |
| | ASCII | GS | (| k | pL | pH | 1 | Q | 1 |
| [Range] | (pL + pH × 256) = 3 (pL = 0x03, pH = 0x00) | | | | | | | | |
| [Description] | Prints the data stored in the barcode save area in QRcode format. | | | | | | | | |
| [Notes] | pL and pH specify the number of successive bytes to be sent. | | | | | | | | |
| [Default] | | | | | | | | | |
| [Reference] | 0x1D 0x28 0x6B | | | | | | | | |
| [Example] | | | | | | | | | |



0x1D 0x28 0x6B [Fn 182]

<GS (k>

Transmit the QRcode barcode size in the barcode save area

| | | | | | | | | | |
|---------------|---|----|----|----|----|----|----|----|----|
| Valid for | P3 | | | | | | | | |
| [Format] | Hex | 1D | 28 | 6B | pL | pH | 31 | 52 | 30 |
| | ASCII | GS | (| k | pL | pH | 1 | R | 0 |
| [Range] | (pL+pH × 256) = 3 (pL = 0x03, pH = 0x00) | | | | | | | | |
| [Description] | Transmits the QRcode barcode size in the barcode save area. | | | | | | | | |
| [Notes] | <ul style="list-style-type: none"> To store the data in the device barcode save area use the Function 180. In standard mode, use this function when device is at the beginning of a line or when there is no data in the print buffer. pL and pH specify the number of successive bytes to be sent. The size information for each data is as follows: | | | | | | | | |

| SEND DATA | HEX | DATA |
|----------------------------------|----------|------------|
| Header | 37 | 1 byte |
| Identifier | 36 | 1 byte |
| Horizontal size ⁽¹⁾ | 30-39 | 1 - 5 byte |
| Separator | 1F | 1 byte |
| Vertical size ⁽¹⁾ | 30-39 | 1 - 5 byte |
| Separator | 1F | 1 byte |
| Fixed value | 31 | 1 byte |
| Separator | 1F | 1 byte |
| Other information ⁽²⁾ | 30 or 31 | 1 byte |
| NUL | 00 | 1 byte |

(1) "Horizontal size" and "vertical size" indicate the number of dots of the symbol.

The values of the vertical size and horizontal size are converted to characters and sent starting from the high order end (ex: When horizontal size is 120 dots, horizontal size is 0x31 0x32 0x30, which is 3 bytes of data).

(2) "Other information" indicates whether printing of the data in the symbol storage area is possible or impossible. The "Other information" is the following:

| HEX | CONDITION |
|-----|------------------------|
| 30 | Printing is possible |
| 31 | Printing is impossible |



- Size information indicates size of symbol that is printed by [Function 181](#).
- The quiet zone is not included in the size information.
- If “other information” is “Printing is impossible”(0x31), use one of the solutions shown below:

| CAUSE | SOLUTION |
|---|--|
| There are data in the print buffer in the standard mode | Clear the data in the print buffer by executing 0x0A , 0x0D , 0x1B 0x4A print commands. |
| Symbol is bigger than the current print area. | Expand the print area by 0x1D 0x57 , 0x1B 0x24 . Reduce the module size by using Function 167 . Lower the error correction level by using Function 169 . |
| The data in the symbol storage area is too large. | Send correct data by using Function 180 . Lower the error correction level by using Function 169 . |
| There is no data in the symbol storage area. | Send data to the symbol storage area by using Function 180 . |

[Default]

[Reference]

[0x1D](#) [0x28](#) [0x6B](#)

[Example]

A possible device response can be:

[0x37](#) [0x36](#) [0x31](#) [0x32](#) [0x36](#) [0x1F](#) [0x31](#) [0x32](#) [0x36](#) [0x1F](#) [0x31](#) [0x1F](#) [0x30](#) [0x00](#)

where:

| | |
|--|--|
| 0x37 | header |
| 0x36 | identifier |
| 0x31 0x32 0x36 | horizontal size 126 dots (0x31 = 1, 0x32 = 2, 0x36 = 6) |
| 0x1F | separator |
| 0x31 0x32 0x36 | vertical size 126 dots (0x31 = 1, 0x32 = 2, 0x36 = 6) |
| 0x1F | separator |
| 0x31 | fixed value |
| 0x1F | separator |
| 0x30 | printing possible |
| 0x00 | NUL (end of text character) |



0x1D 0x28 0x6B [Fn Q65]

<GS (k>

Specify the encoding scheme of DATAMATRIX barcode

| Valid for | P3 | | | | | | | | | | | | | | | | | | | | | | | | |
|---------------|---|----|----|----|----|----|----|----|---|---|----------|------|-------|------|-----|------|------|------|-----|------|---------|------|---------|------|----------|
| [Format] | Hex | 1D | 28 | 6B | pL | pH | 51 | 41 | n | | | | | | | | | | | | | | | | |
| | ASCII | GS | (| k | pL | pH | Q | A | n | | | | | | | | | | | | | | | | |
| [Range] | (pL + pH × 256) = 3 (pL = 0x03, pH = 0x00) 0x00 ≤ n ≤ 0x06 | | | | | | | | | | | | | | | | | | | | | | | | |
| [Description] | Set the encoding scheme for the DATAMATRIX barcode based on the value of n as follows: | | | | | | | | | | | | | | | | | | | | | | | | |
| | <table><tr><th>n</th><th>ENCODING</th></tr><tr><td>0x00</td><td>ASCII</td></tr><tr><td>0x01</td><td>C40</td></tr><tr><td>0x02</td><td>Text</td></tr><tr><td>0x03</td><td>X12</td></tr><tr><td>0x04</td><td>Edifact</td></tr><tr><td>0x05</td><td>Base256</td></tr><tr><td>0x06</td><td>AutoBest</td></tr></table> | | | | | | | | | n | ENCODING | 0x00 | ASCII | 0x01 | C40 | 0x02 | Text | 0x03 | X12 | 0x04 | Edifact | 0x05 | Base256 | 0x06 | AutoBest |
| n | ENCODING | | | | | | | | | | | | | | | | | | | | | | | | |
| 0x00 | ASCII | | | | | | | | | | | | | | | | | | | | | | | | |
| 0x01 | C40 | | | | | | | | | | | | | | | | | | | | | | | | |
| 0x02 | Text | | | | | | | | | | | | | | | | | | | | | | | | |
| 0x03 | X12 | | | | | | | | | | | | | | | | | | | | | | | | |
| 0x04 | Edifact | | | | | | | | | | | | | | | | | | | | | | | | |
| 0x05 | Base256 | | | | | | | | | | | | | | | | | | | | | | | | |
| 0x06 | AutoBest | | | | | | | | | | | | | | | | | | | | | | | | |
| [Notes] | pL and pH specify the number of successive bytes to be sent. | | | | | | | | | | | | | | | | | | | | | | | | |
| [Default] | | | | | | | | | | | | | | | | | | | | | | | | | |
| [Reference] | 0x1D 0x28 0x6B | | | | | | | | | | | | | | | | | | | | | | | | |
| [Example] | To set encoding = ASCII, the command sequence is: 0x1D 0x28 0x6B 0x03 0x00 0x51 0x41 0x00 | | | | | | | | | | | | | | | | | | | | | | | | |



0x1D 0x28 0x6B [Fn Q66]

<GS (k>

Set rotation of DATAMATRIX barcode

| | | | | | | | | | |
|-----------|----|--|--|--|--|--|--|--|--|
| Valid for | P3 | | | | | | | | |
|-----------|----|--|--|--|--|--|--|--|--|

| | | | | | | | | | |
|----------|-------|----|----|----|----|----|----|----|---|
| [Format] | Hex | 1D | 28 | 6B | pL | pH | 51 | 42 | n |
| | ASCII | GS | (| k | pL | pH | Q | B | n |

| | | | | | | | | | |
|---------|--|--|--|--|--|--|--|--|--|
| [Range] | (pL + pH × 256) = 3 (pL = 0x03, pH = 0x00) n = 0x00, 0x01 | | | | | | | | |
|---------|--|--|--|--|--|--|--|--|--|

| | | | | | | | | | |
|---------------|---|--|--|--|--|--|--|--|--|
| [Description] | Set the rotation for the DATAMATRIX barcode based on the value of n as follows: | | | | | | | | |
|---------------|---|--|--|--|--|--|--|--|--|

| n | ROTATION |
|------|-------------|
| 0x00 | No rotation |
| 0x01 | Rotation |

| | | | | | | | | | |
|---------|--|--|--|--|--|--|--|--|--|
| [Notes] | pL and pH specify the number of successive bytes to be sent. | | | | | | | | |
|---------|--|--|--|--|--|--|--|--|--|

| | | | | | | | | | |
|-----------|--|--|--|--|--|--|--|--|--|
| [Default] | | | | | | | | | |
|-----------|--|--|--|--|--|--|--|--|--|

| | | | | | | | | | |
|-------------|----------------|--|--|--|--|--|--|--|--|
| [Reference] | 0x1D 0x28 0x6B | | | | | | | | |
|-------------|----------------|--|--|--|--|--|--|--|--|

| | | | | | | | | | |
|-----------|--|--|--|--|--|--|--|--|--|
| [Example] | | | | | | | | | |
|-----------|--|--|--|--|--|--|--|--|--|



0x1D 0x28 0x6B [Fn Q67]

<GS (k>

Set dot size of the module of DATAMATRIX barcode

| | | | | | | | | | |
|---------------|---|----|----|----|----|----|----|----|---|
| Valid for | P3 | | | | | | | | |
| [Format] | Hex | 1D | 28 | 6B | pL | pH | 51 | 43 | n |
| | ASCII | GS | (| k | pL | pH | Q | C | n |
| [Range] | (pL + pH × 256) = 3 (pL = 0x03, pH = 0x00) 0x02 ≤ n ≤ 0x18 | | | | | | | | |
| [Description] | Set dot size of the module of the DATAMATRIX barcode: n = dot dimension | | | | | | | | |
| [Notes] | pL and pH specify the number of successive bytes to be sent. | | | | | | | | |
| [Default] | n = 0x06 | | | | | | | | |
| [Reference] | 0x1D 0x28 0x6B | | | | | | | | |
| [Example] | To set dot size = 6 the command sequence is: 0x1D 0x28 0x6B 0x03 0x00 0x51 0x43 0x06 | | | | | | | | |



0x1D 0x28 0x6B [Fn Q68]

<GS (k>

Set size of DATAMATRIX barcode

| | |
|-----------|----|
| Valid for | P3 |
|-----------|----|

| | | | | | | | | | |
|----------|---|----|----|----|----|----|----|----|---|
| [Format] | Hex | 1D | 28 | 6B | pL | pH | 51 | 44 | n |
| | ASCII | GS | (| k | pL | pH | Q | D | n |
| [Range] | (pL + pH × 256) = 3 (pL = 0x03, pH = 0x00) 0x00 ≤ n ≤ 0x1D | | | | | | | | |

| | |
|---------------|--|
| [Description] | Set the size of DATAMATRIX barcode based on the value of n as follows: |
|---------------|--|

| n | BARCODE SIZE | n | BARCODE SIZE |
|------|--------------|------|--------------|
| 0x00 | AUTO | 0x0F | 52 x 52 |
| 0x01 | 10 x 10 | 0x10 | 64 x 64 |
| 0x02 | 12 x 12 | 0x11 | 72 x 72 |
| 0x03 | 14 x 14 | 0x12 | 80 x 80 |
| 0x04 | 16 x 16 | 0x13 | 88 x 88 |
| 0x05 | 18 x 18 | 0x14 | 96 x 96 |
| 0x06 | 20 x 20 | 0x15 | 104 x 104 |
| 0x07 | 22 x 22 | 0x16 | 120 x 120 |
| 0x08 | 24 x 24 | 0x17 | 132 x 132 |
| 0x09 | 26 x 26 | 0x18 | 144 x 144 |
| 0x0A | 32 x 32 | 0x19 | 8 x 18 |
| 0x0B | 36 x 36 | 0x1A | 8 x 32 |
| 0x0C | 40 x 40 | 0x1B | 12 x 26 |
| 0x0D | 44 x 44 | 0x1C | 12 x 36 |
| 0x0E | 48 x 48 | 0x1D | 16 x 36 |

| | |
|---------|--|
| [Notes] | pL and pH specify the number of successive bytes to be sent. |
|---------|--|

| | |
|-----------|----------|
| [Default] | n = 0x00 |
|-----------|----------|

| | |
|-------------|----------------|
| [Reference] | 0x1D 0x28 0x6B |
|-------------|----------------|

| | |
|-----------|--|
| [Example] | |
|-----------|--|



0x1D 0x28 0x6B [Fn Q80]

<GS (k>

Store the DATAMATRIX barcode data in the barcode save area

| | | | | | | | | | | |
|---------------|--|----|----|----|----|----|----|----|----|---------|
| Valid for | P3 | | | | | | | | | |
| [Format] | Hex | 1D | 28 | 6B | pL | pH | 51 | 50 | 33 | d1...dk |
| | ASCII | GS | (| k | pL | pH | Q | P | 3 | d1...dk |
| [Range] | <p>$0x00 \leq d \leq 0xFF$ $k = (pL + pH \times 256) - 3$</p> <ul style="list-style-type: none"> DATAMATRIX barcode only with ASCII characters (8 bit) : $4 \leq (pL + pH \times 256) \leq 1560$ ($0x00 \leq pL \leq 0xFF$, $0x00 \leq pH \leq 0x06$) DATAMATRIX barcode only with alphanumeric characters: $4 \leq (pL + pH \times 256) \leq 2339$ ($0x00 \leq pL \leq 0xFF$, $0x00 \leq pH \leq 0x09$) DATAMATRIX barcode only with numeric characters: $4 \leq (pL + pH \times 256) \leq 3120$ ($0x00 \leq pL \leq 0xFF$, $0x00 \leq pH \leq 0x0C$) | | | | | | | | | |
| [Description] | Store the DATAMATRIX barcode data (d1...dk) in the barcode save area. | | | | | | | | | |
| [Notes] | <ul style="list-style-type: none"> Data stored in the barcode save area by this function are processed by Function Q81 and then reserved. pL and pH specify the number of successive bytes to be sent. k bytes of d1...dk are processed as barcode data. Specify only the data code word of the barcode with this function. Be sure not to include the control data in the data d1...dk because they are added automatically by the device. | | | | | | | | | |
| [Default] | | | | | | | | | | |
| [Reference] | 0x1D 0x28 0x6B | | | | | | | | | |
| [Example] | | | | | | | | | | |



0x1D 0x28 0x6B [Fn Q81]

<GS (k>

Encodes and prints the data stored in the barcode save area in DATAMATRIX format

| | | | | | | | | | |
|---------------|---|----|----|----|----|----|----|----|----|
| Valid for | P3 | | | | | | | | |
| [Format] | Hex | 1D | 28 | 6B | pL | pH | 51 | 51 | 33 |
| | ASCII | GS | (| k | pL | pH | Q | Q | 3 |
| [Range] | (pL + pH × 256) = 3 (pL = 0x03, pH = 0x00) | | | | | | | | |
| [Description] | Encodes and prints the data stored in the barcode save area in DATAMATRIX format. | | | | | | | | |
| [Notes] | <ul style="list-style-type: none">• In standard mode, use this function when device is at the beginning of a line or there is no data in the print buffer.• pL and pH specify the number of successive bytes to be sent.• A barcode that size exceeds the printing area cannot be printed.• If there is any error described below in the data of the barcode save area, it cannot be printed.<ul style="list-style-type: none">- There is no data (Function Q80 is not processed).- If [(number of columns × number of rows) < number of code word] when auto processing is specified for number of columns and number of rows.- Number of code word exceeds 928 in the data area.• When auto processing (Function Q65) is specified, the number of columns is calculated by the current printing area, module width (Function Q67) and the code word in the data area. Maximum number of the columns is 30. | | | | | | | | |
| [Default] | | | | | | | | | |
| [Reference] | 0x1D 0x28 0x6B | | | | | | | | |
| [Example] | To print the DATAMATRIX barcode data the command sequence is: 0x1D 0x28 0x6B 0x03 0x00 0x51 0x51 0x33 | | | | | | | | |



0x1D 0x48

<GS H>


Select printing position of HRI characters in 1D barcodes

| Valid for | P3 | | | | | | | | | | | | | |
|---------------|--|----|----|---|---|----------|------------|-------------|------------|-------------------|------------|-------------------|------------|----------------------------------|
| [Format] | Hex | 1D | 48 | n | | | | | | | | | | |
| | ASCII | GS | H | n | | | | | | | | | | |
| [Range] | 0x00 ≤ n ≤ 0x03 0x30 ≤ n ≤ 0x33 | | | | | | | | | | | | | |
| [Description] | Selects the print position of HRI (Human Readable Interpretation) characters when printing a 1D barcode, based on the value of n as follows: | | | | | | | | | | | | | |
| | <table><tr><th>n</th><th>FUNCTION</th></tr><tr><td>0x00, 0x30</td><td>Not printed</td></tr><tr><td>0x01, 0x31</td><td>Above the barcode</td></tr><tr><td>0x02, 0x32</td><td>Below the barcode</td></tr><tr><td>0x03, 0x33</td><td>Both above and below the barcode</td></tr></table> | | | | n | FUNCTION | 0x00, 0x30 | Not printed | 0x01, 0x31 | Above the barcode | 0x02, 0x32 | Below the barcode | 0x03, 0x33 | Both above and below the barcode |
| n | FUNCTION | | | | | | | | | | | | | |
| 0x00, 0x30 | Not printed | | | | | | | | | | | | | |
| 0x01, 0x31 | Above the barcode | | | | | | | | | | | | | |
| 0x02, 0x32 | Below the barcode | | | | | | | | | | | | | |
| 0x03, 0x33 | Both above and below the barcode | | | | | | | | | | | | | |
| [Notes] | HRI characters are printed using the font specified by 0x1D 0x66 . | | | | | | | | | | | | | |
| [Default] | n = 0x00 | | | | | | | | | | | | | |
| [Reference] | 0x1D 0x66 , 0x1D 0x6B | | | | | | | | | | | | | |



[Example]

Not printed




Above the barcode

ABCDEFGH123456




Below the barcode



ABCDEFGH123456

Both above and below the barcode

ABCDEFGH123456



ABCDEFGH123456



0x1D 0x66

<GS f>

Select font for HRI characters

| Valid for | P3 | | | | | | | | | |
|---------------|--|----|----|---|---|------|------------|--------|------------|--------|
| [Format] | Hex | 1D | 66 | n | | | | | | |
| | ASCII | GS | f | n | | | | | | |
| [Range] | n = 0x00, 0x01, 0x30, 0x31 | | | | | | | | | |
| [Description] | Selects a font for the HRI (Human Readable Interpretation) characters used when printing a 1D barcode, based on the value of n as follows: | | | | | | | | | |
| | <table><tr><th>n</th><th>FONT</th></tr><tr><td>0x00, 0x30</td><td>Font A</td></tr><tr><td>0x01, 0x31</td><td>Font B</td></tr></table> | | | | n | FONT | 0x00, 0x30 | Font A | 0x01, 0x31 | Font B |
| n | FONT | | | | | | | | | |
| 0x00, 0x30 | Font A | | | | | | | | | |
| 0x01, 0x31 | Font B | | | | | | | | | |
| [Notes] | HRI characters are printed at the position specified by 0x1D 0x48. | | | | | | | | | |
| [Default] | n = 0x00 | | | | | | | | | |
| [Reference] | 0x1D 0x48, 0x1D 0x6B | | | | | | | | | |
| [Example] | | | | | | | | | | |

Font A



Font B





0x1D 0x68

<GS h>

Set 1D barcode height

| | | | | |
|---------------|--|----|----|---|
| Valid for | P3 | | | |
| [Format] | Hex | 1D | 68 | n |
| | ASCII | GS | h | n |
| [Range] | 0x01 ≤ n ≤ 0xFF | | | |
| [Description] | Sets the height of the 1D barcode. n specifies the number of vertical dots. | | | |
| [Notes] | | | | |
| [Default] | n = 0xA2 (20.25 mm) | | | |
| [Reference] | 0x1D 0x6B | | | |
| [Example] | To print a barcode with height of 15 mm, the command sequence is: 0x1D 0x68 0x78 | | | |
| | Where: 15 mm = 15 × 8 dots = 120 dots which converted in hexadecimal value = 0x78 | | | |



0x1D 0x6B

<GS k>

Print 1D barcode

| | | | | | | |
|---------------|---|------------------|----|---|----------|----------|
| Valid for | P3 | | | | | |
| [Format 1] | Hex | 1D | 6B | m | [d1..dk] | 00 |
| | ASCII | GS | k | m | [d1..dk] | NUL |
| [Format 2] | Hex | 1D | 6B | m | n | [d1..dn] |
| | ASCII | GS | k | m | n | [d1..dn] |
| [Range] | Format 1 | 0x00 ≤ m ≤ 0x08, | | | m = 0x14 | |
| | Format 2 | 0x41 ≤ m ≤ 0x49, | | | m = 0x5A | |
| [Description] | Selects a 1D barcode system and prints the 1D barcode based on the value of m as follows: | | | | | |

Format 1

| m | BARCODE SYSTEM | NUMBER OF CHARACTERS | REMARKS |
|------|----------------|------------------------|---|
| 0x00 | UPC-A | 0x0B ≤ k ≤ 0x0C | 0x30 ≤ d ≤ 0x39 |
| 0x01 | UPC-E | 0x0B ≤ k ≤ 0x0C | 0x30 ≤ d ≤ 0x39 |
| 0x02 | EAN13 (JAN) | 0x0C ≤ k ≤ 0x0D | 0x30 ≤ d ≤ 0x39 |
| 0x03 | EAN8 (JAN) | 0x07 ≤ k ≤ 0x08 | 0x30 ≤ d ≤ 0x39 |
| 0x04 | CODE39 | 0x01 ≤ k | 0x30 ≤ d ≤ 0x39, 0x41 ≤ d ≤ 0x5A, 0x20, 0x24, 0x25, 0x2B, 0x2D, 0x2E, 0x2F |
| 0x05 | ITF | 0x01 ≤ k (even number) | 0x30 ≤ d ≤ 0x39 |
| 0x06 | CODABAR | 0x01 ≤ k | 0x30 ≤ d ≤ 0x39, 0x41 ≤ d1 ≤ 0x44, 0x24, 0x2B, 0x2D, 0x2E, 0x2F, 0x3A |
| 0x07 | CODE93 | 0x01 ≤ k ≤ 0xFF | 0x01 ≤ d ≤ 0x7F |
| 0x08 | CODE128 | 0x02 ≤ k ≤ 0xFF | 0x01 ≤ d ≤ 0x7F |
| 0x14 | CODE32 | 0x08 ≤ k ≤ 0x09 | 0x30 ≤ d ≤ 0x39 |



Format 2

| m | BARCODE SYSTEM | NUMBER OF CHARACTERS | REMARKS |
|------|----------------|-------------------------|--|
| 0x41 | UPC-A | $0x0B \leq n \leq 0x0C$ | $0x30 \leq d \leq 0x39$ |
| 0x42 | UPC-E | $0x0B \leq n \leq 0x0C$ | $0x30 \leq d \leq 0x39$ |
| 0x43 | EAN13 (JAN) | $0x0C \leq n \leq 0x0D$ | $0x30 \leq d \leq 0x39$ |
| 0x44 | EAN8 (JAN) | $0x07 \leq n \leq 0x08$ | $0x30 \leq d \leq 0x39$ |
| 0x45 | CODE39 | $0x01 \leq n \leq 0xFF$ | $0x30 \leq d \leq 0x39$, $0x41 \leq d \leq 0x5A$, $0x20, 0x24, 0x25, 0x2B$, $0x2D, 0x2E, 0x2F$ |
| 0x46 | ITF | $0x01 \leq n \leq 0xFF$ | $0x30 \leq d \leq 0x39$ |
| 0x47 | CODABAR | $0x01 \leq n \leq 0xFF$ | $0x30 \leq d \leq 0x39$, $0x41 \leq d1 \leq 0x44$, $0x24, 0x2B, 0x2D$, $0x2E, 0x2F, 0x3A$ |
| 0x48 | CODE93 | $0x01 \leq n \leq 0xFF$ | $0x01 \leq d \leq 0x7F$ |
| 0x49 | CODE128 | $0x02 \leq n \leq 0xFF$ | $0x01 \leq d \leq 0x7F$ |
| 0x5A | CODE32 | $0x08 \leq n \leq 0x09$ | $0x30 \leq d \leq 0x39$ |

[Notes]

- If d is outside of the specified range, the device prints the following message: "BARCODE GENERATOR IS NOT OK!" and processes the data which follows as normal data.
- If the horizontal size exceeds the printing area, the device only feeds the paper.
- This command feeds as much paper as is required to print the barcode, regardless of the line spacing specified by [0x1B 0x32](#) or [0x1B 0x33](#).
- After printing the barcode, this command sets the print position to the beginning of the line.
- This command is not affected by print modes (bold, double-strike, underline or character size), except for upside-down and justification mode.

Format 1

- This command ends with a NUL code.
- When the barcode system used is UPC-A or UPC-E, the device prints the barcode data after receiving 11 (without check digit) or 12 (with check digit) bytes barcode data.
- When the barcode system used is EAN13, the device prints the barcode data after receiving 12 (without check digit) or 13 (with check digit) bytes barcode data.
- When the barcode system used is EAN8, the device prints the barcode data after receiving 7 (without check digit) or 8 (with check digit) bytes barcode data.
- The number of data for ITF barcode must be even numbers. When an odd number of data is input, the device ignores the last received data.

Format 2

If n is outside of the specified range, the device stops command processing and processes the following data as normal data.

When CODE93 is used:

- The device prints an HRI character (o) as a start character at the beginning of the HRI character string.



- The device prints an HRI character (o) as a stop character at the end of the HRI character string.
- The device prints an HRI character (n) as a control character (0x00 to 0x1F and 0x7F).

When CODE128 is used, please note the following regarding data transmission:

- The top part of the barcode data string must be a code set selection character (CODE A, CODE B or CODE C) which selects the first code set.
- Special characters are defined by combining two characters “{” and one character. ASCII character “{” is defined by transmitting “{” twice, consecutively.

| SPECIFIC CHARACTER | DATA TRANSMISSION | |
|--------------------|-------------------|--------|
| | ASCII | HEX |
| SHIFT | {S | 7B, 53 |
| CODE A | {A | 7B, 41 |
| CODE B | {B | 7B, 42 |
| CODE C | {C | 7B, 43 |
| FNC1 | {1 | 7B, 31 |
| FNC2 | {2 | 7B, 32 |
| FNC3 | {3 | 7B, 33 |
| FNC4 | {4 | 7B, 34 |
| {“ | {{ | 7B, 7B |

When UPC-E is used, introducing the barcode characters, the device prints:

| TRANSMITTED DATA | | | | | | | | | | | PRINTED DATA | | | | | |
|------------------|-----|-----|-----|-----|-----|----|----|-----|-----|-----|--------------|----|----|-----|-----|-----|
| d1 | d2 | d3 | d4 | d5 | d6 | d7 | d8 | d9 | d10 | d11 | | | | | | |
| 0 | 0-9 | 0-9 | 0 | 0 | 0 | 0 | 0 | 0-9 | 0-9 | 0-9 | d2 | d3 | d9 | d10 | d11 | 0 |
| 0 | 0-9 | 0-9 | 1 | 0 | 0 | 0 | 0 | 0-9 | 0-9 | 0-9 | d2 | d3 | d9 | d10 | d11 | 1 |
| 0 | 0-9 | 0-9 | 2 | 0 | 0 | 0 | 0 | 0-9 | 0-9 | 0-9 | d2 | d3 | d9 | d10 | d11 | 2 |
| 0 | 0-9 | 0-9 | 3-9 | 0 | 0 | 0 | 0 | 0 | 0-9 | 0-9 | d2 | d3 | d4 | d10 | d11 | 3 |
| 0 | 0-9 | 0-9 | 0-9 | 1-9 | 0 | 0 | 0 | 0 | 0 | 0-9 | d2 | d3 | d4 | d5 | d11 | 4 |
| 0 | 0-9 | 0-9 | 0-9 | 0-9 | 1-9 | 0 | 0 | 0 | 0 | 5-9 | d2 | d3 | d4 | d5 | d6 | d11 |

[Default]

[Reference]

0x1D 0x48, 0x1D 0x68, 0x1D 0x77

[Example]

Format 1: Example for printing a CODE39 barcode:
0x1D 0x6B 0x04 0x54 0x45 0x53 0x54 0x00

Format 2: Example for printing a CODE39 barcode:
0x1D 0x6B 0x45 0x04 0x54 0x45 0x53 0x54



0x1D 0x77

<GS w>

Set 1D barcode width

| | | | | |
|-----------|----|--|--|--|
| Valid for | P3 | | | |
|-----------|----|--|--|--|

| | | | | |
|----------|-------|----|----|---|
| [Format] | Hex | 1D | 77 | n |
| | ASCII | GS | w | n |

| | |
|---------|-------------------------|
| [Range] | $0x01 \leq n \leq 0x06$ |
|---------|-------------------------|

| | |
|---------------|---|
| [Description] | Sets the horizontal size of the 1D barcode. n specifies the barcode width as follows: |
|---------------|---|

| n | MODULE WIDTH (mm) |
|------|-------------------|
| 0x01 | 0.125 |
| 0x02 | 0.25 |
| 0x03 | 0.375 |
| 0x04 | 0.5 |
| 0x05 | 0.625 |
| 0x06 | 0.75 |

| n | | WIDE BAR / NARROW BAR RATIO |
|-------------|------------------------------------|-----------------------------|
| If n < 0x80 | 0x01, 0x02, 0x03, 0x04, 0x05, 0x06 | 3:1 |
| | 0x81 | 3:1 |
| | 0x82 | 2.5:1 |
| If n > 0x80 | 0x83 | 2.33:1 |
| | 0x84 | 2.25:1 |
| | 0x85 | 3:1 |
| | 0x86 | 3:1 |

| | |
|---------|--|
| [Notes] | This command is enabled only when inserted at the beginning of a line. |
|---------|--|


[Default]

n = 0x03


[Reference]

0x1D 0x6B

[Example]



n = 0x01



n = 0x03



CHARACTER COMMANDS

0x18

<CAN>

Cancel current line transmitted

| | | |
|---|-------|-----|
| Valid for | P3 | |
| [Format] | Hex | 18 |
| | ASCII | CAN |
| [Range] | | |
| [Description] | | |
| Deletes current line transmitted. | | |
| [Notes] | | |
| <ul style="list-style-type: none">• Sets the print position to the beginning of the line.• This command does not clear the receive buffer. | | |
| [Default] | | |
| [Reference] | | |
| [Example] | | |



0x1B 0x20

Set right-side character spacing

| | | | | |
|---------------|---|-----|----|---|
| Valid for | P3 | | | |
| [Format] | Hex | 1B | 20 | n |
| | ASCII | ESC | SP | n |
| [Range] | $0x00 \leq n \leq 0xFF$ | | | |
| [Description] | Sets the character spacing for the right side of the character to $[n \times \text{horizontal or vertical motion units}]$. | | | |
| [Notes] | <ul style="list-style-type: none">• The right character spacing for double-width mode is twice the normal value. When the characters are enlarged, the right side character spacing is m (2 or 4) times the normal value.• The horizontal and vertical motion units are specified by 0x1D 0x50. Changing the horizontal or vertical motion units does not affect the current right side spacing.• The 0x1D 0x50 command can change the horizontal (and vertical) motion unit. However, the value cannot be less than the minimum horizontal movement amount.• The maximum right side spacing is 32 mm.• In standard mode, the horizontal motion unit is used. | | | |
| [Default] | n = 0x00 | | | |
| [Reference] | 0x1D 0x50 | | | |

[Example]

Character spacing x0
0x1B 0x20 0x00

Character spacing x2
0x1B 0x20 0x02

Character spacing x4
0x1B 0x20 0x04

Character spacing x8
0x1B 0x20 0x08

ABCDEFGH
1 2 3 4 5 6

ABCDEFGH
1 2 3 4 5 6

ABCDEFGH
1 2 3 4 5 6

A B C D E F G
1 2 3 4 5 6

PRINTING DIRECTION



0x1B 0x21

<ESC !>

Select print modes

| | | | | |
|-----------|----|--|--|--|
| Valid for | P3 | | | |
|-----------|----|--|--|--|

| | | | | |
|----------|-------|-----|----|---|
| [Format] | Hex | 1B | 21 | n |
| | ASCII | ESC | ! | n |

| | |
|---------|-----------------|
| [Range] | 0x00 ≤ n ≤ 0xFF |
|---------|-----------------|

| | |
|---------------|---|
| [Description] | Selects print modes based on the value of n as follows: |
|---------------|---|

| BIT | OFF/ON | n | FUNCTION | 11/15 dpi | 15/20 dpi |
|-----|--------|------|---------------------------------|--------------|--------------|
| 0 | Off | 0x00 | Character font A selected | 18 x 24 | 14 x 24 |
| | On | 0x01 | Character font B selected | 14 x 24 | 10 x 24 |
| 1 | - | - | Undefined | | |
| 2 | - | - | Undefined | | |
| 3 | Off | 0x00 | Bold mode not selected | | |
| | On | 0x08 | Blod mode selected | | |
| 4 | Off | 0x00 | Double-height mode not selected | | |
| | On | 0x10 | Double-height mode selected | | |
| 5 | Off | 0x00 | Double-width mode not selected | | |
| | On | 0x20 | Double-width mode selected | | |
| 6 | Off | 0x00 | Italic mode not selected | | |
| | On | 0x40 | Italic mode selected | | |
| 7 | Off | 0x00 | Underlined mode not selected | | |
| | On | 0x80 | Underlined mode selected | | |

| | |
|---------|--|
| [Notes] | • The device can underline all characters, but cannot underline the spaces set by 0x09, 0x1B 0x24, 0x1B 0x5C and 90°/270° rotated characters. |
| | • This command resets the left and right margin at default value (see 0x1D 0x4C, 0x1D 0x57). |
| | • 0x1B 0x45 can also be used to turn the bold mode on or off. However, the last-received setting command is the effective one. |
| | • 0x1B 0x2D can also be used to turn the underlining mode on or off. However, the last-received setting command is the effective one. |
| | • 0x1D 0x21 can also be used to select character height or width. However, the last-received setting command is the effective one. |
| | • 0x1B 0x34 can also be used to turn the italic mode on or off. However, the last-received setting command is the effective one. |
| | • Commands that change the height and width of characters are effective on the x and y axes. In case of 90°/270° rotated characters, command 0x1B 0x21 0x10 selects double-width mode and command 0x1B 0x21 0x20 selects double-height mode. |
| | |



[Default]

n = 0x00

[Reference]

0x1B 0x2D, 0x1B 0x45, 0x1D 0x21, 0x1B 0x34

[Example]

Character font A selected
0x1B 0x21 0x00

ABCDEFGH
123456

Character font B selected
0x1B 0x21 0x01

ABCDEFGH
123456

Bold mode selected
0x1B 0x21 0x08

ABCDEFGH
123456

Double-height mode selected
0x1B 0x21 0x10

ABCDEFGH
123456

Double-width mode selected
0x1B 0x21 0x20

ABCDEFGH
1 2 3 4 5 6

Italic mode selected
0x1B 0x21 0x40

ABCDEFGH
123456

Underline mode selected
0x1B 0x21 0x80

ABCDEFGH
123456





0x1B 0x25

<ESC %>

Enable or disable user-defined characters

| | | | | |
|---------------|---|-----|----|---|
| Valid for | P3 | | | |
| [Format] | Hex | 1B | 25 | n |
| | ASCII | ESC | % | n |
| [Range] | 0x00 ≤ n ≤ 0xFF | | | |
| [Description] | <p>Enables or disables the user-defined character set.</p> <p>When the Least Significant Bit (LSB) of n is 0, the user-defined character set is disabled.</p> <p>When the Least Significant Bit (LSB) of n is 1, the user-defined character set is enabled.</p> | | | |
| [Notes] | <ul style="list-style-type: none">• Only the Least Significant Bit (LSB) of n is applicable.• When the user-defined character set is disabled, the internal character set is automatically selected. | | | |
| [Default] | n = 0x00 | | | |
| [Reference] | 0x1B 0x26, 0x1B 0x3F | | | |
| [Example] | | | | |



0x1B 0x26

<ESC &>

Defines user-defined characters

| Valid for | P3 | | | | | | |
|---------------|--|-----|----|---|----|----|-----------------------------|
| [Format] | Hex | 1B | 26 | y | c1 | cn | x1[d0...dk] ... xn[d0...dk] |
| | ASCII | ESC | & | y | c1 | cn | x1[d0...dk] ... xn[d0...dk] |
| [Range] | y = 0x03 $0x20 \leq c1 \leq cn \leq 0x7E$ $0x00 \leq x \leq 0x12$ (font 18 x 24) $0x00 \leq x \leq 0x0E$ (font 14 x 24) $0x00 \leq x \leq 0x0A$ (font 10 x 24) $0x00 \leq x \leq 0x08$ (font 8 x 24) $0x00 \leq d0...dk \leq 0xFF$ $k = cn - c1 + 1$ | | | | | | |
| [Description] | Defines user programmable characters. y specifies the number of bytes in the vertical direction. c1 specifies the start character code and cn specifies the final character code of the characters map area. x specifies the width of the character to be replaced. d0...dk specifies the new character definition. | | | | | | |
| [Notes] | <ul style="list-style-type: none"> It is possible to define multiple characters for consecutive character codes. If only one character is desired, use $c1 = cn$. if $cn < c1$, the command is not executed. d is the dot data for the characters. The dot pattern is in the horizontal direction starting from the left. Any remaining dots on the right remain blank. The data to define a user-defined character is $(x \times y)$ bytes. To print a dot, set the corresponding bit to 1; to not have it print, set to 0. This command can define different user-defined character patterns for each font. To select the font, use 0x1B 0x21. The user programmable character definitions are cleared when commands 0x1B 0x40, 0x1D 0x2A or 0x1B 0x3F are executed or the device is reset or turned off. x1 [d0 ... dk] will be repeated for each character to be replaced. | | | | | | |
| [Default] | Internal character set | | | | | | |
| [Reference] | 0x1B 0x25 , 0x1B 0x3F | | | | | | |
| [Example] | To replace only the "A" character of the 11 cpi font table (font 18x24), the command sequence is: 0x1B 0x26 0x03 0x41 0x41 0x10 [48 bytes of the new character definition]. To replace "A" and "B" characters of the 11 cpi font table (font 18x24), the command sequence is: 0x1B 0x26 0x03 0x41 0x42 0x10 [48 bytes of the new character definition] 0x10 [48 bytes of the new character definition]. | | | | | | |



0x1B 0x2D

<ESC ->

Turn underline mode on or off

| | | | | |
|-----------|----|--|--|--|
| Valid for | P3 | | | |
|-----------|----|--|--|--|

| | | | | |
|----------|-------|-----|----|---|
| [Format] | Hex | 1B | 2D | n |
| | ASCII | ESC | - | n |

| | |
|---------|-------------------------|
| [Range] | $0x00 \leq n \leq 0x02$ |
| | $0x30 \leq n \leq 0x32$ |

[Description] Turns underline mode on or off based on the value of n as follows:


| n | FUNCTION |
|------------|---------------------------------------|
| 0x00, 0x30 | Turns off underline mode |
| 0x01, 0x31 | Turns on underline mode (1 dot thick) |
| 0x02, 0x32 | Turns on underline mode (2 dot thick) |

- [Notes]
- The device can underline all characters, but cannot underline the space and right-side character spacing set by command 0x09.
 - The device cannot underline 90°/270° rotated characters and white/black inverted characters.
 - When underline mode is turned off by setting the value of n to 0x00 or 0x30, the data which follows is not underlined.
 - Underline mode can also be turned on or off by using 0x1B 0x21. However, the last-received setting command is the effective one.

[Default] n = 0x00

[Reference] 0x1B 0x21


[Example]



0x1B 0x34

<ESC 4>

Turn italic mode on or off

| Valid for | P3 | | | | | | | | | |
|---------------|---|-----|----|---|---|----------|------------|-----------------------|------------|----------------------|
| [Format] | Hex | 1B | 34 | n | | | | | | |
| | ASCII | ESC | 4 | n | | | | | | |
| [Range] | 0x00 ≤ n ≤ 0x01 0x30 ≤ n ≤ 0x31 | | | | | | | | | |
| [Description] | Turns italic mode on or off based on the value of n as follows: | | | | | | | | | |
| | <table><tr><th>n</th><th>FUNCTION</th></tr><tr><td>0x00, 0x30</td><td>Turns off italic mode</td></tr><tr><td>0x01, 0x31</td><td>Turns on italic mode</td></tr></table> | | | | n | FUNCTION | 0x00, 0x30 | Turns off italic mode | 0x01, 0x31 | Turns on italic mode |
| n | FUNCTION | | | | | | | | | |
| 0x00, 0x30 | Turns off italic mode | | | | | | | | | |
| 0x01, 0x31 | Turns on italic mode | | | | | | | | | |
| [Notes] | <ul style="list-style-type: none">• The device can print any character in italic mode.• When italic mode is turned off by setting the value of n to 0x00 or 0x30, the data which follows is printed in normal mode.• Italic mode can also be turned on or off using 0x1B 0x21. However, the last-received setting command is the effective one. | | | | | | | | | |
| [Default] | n = 0x00 | | | | | | | | | |
| [Reference] | 0x1B 0x21 | | | | | | | | | |
| [Example] |  | | | | | | | | | |



0x1B 0x3F

<ESC ?>

Cancel user-defined characters

| | | | | |
|---------------|--|-----|----|---|
| Valid for | P3 | | | |
| [Format] | Hex | 1B | 3F | n |
| | ASCII | ESC | ? | n |
| [Range] | 0x20 ≤ n ≤ 0x7E | | | |
| [Description] | Cancels user-defined characters. | | | |
| [Notes] | <ul style="list-style-type: none">• This command cancels the pattern defined for the character code specified by n.• This command deletes the pattern defined for the specified character code in the font selected by 0x1B 0x21.• If the user-defined character has not been defined for the specified character code, the device ignores this command. | | | |
| [Default] | | | | |
| [Reference] | 0x1B 0x26, 0x1B 0x25 | | | |
| [Example] | | | | |



0x1B 0x45

<ESC E>

Turn bold mode on or off

| | | | | |
|---------------|--|-----|----|---|
| Valid for | P3 | | | |
| [Format] | Hex | 1B | 45 | n |
| | ASCII | ESC | E | n |
| [Range] | $0x00 \leq n \leq 0xFF$ | | | |
| [Description] | <p>Turns bold mode on or off, based on the n value:</p> <ul style="list-style-type: none">- when the Least Significant Bit (LSB) of n is 0, the bold mode is off.- when the Least Significant Bit (LSB) of n is 1, the bold mode is on. | | | |
| [Notes] | <ul style="list-style-type: none">• Only the Least Significant Bit (LSB) of n is effective.• 0x1B 0x21 also turns on and off the bold mode. However, the last received command is the effective one. | | | |
| [Default] | n = 0x00 | | | |
| [Reference] | 0x1B 0x21 | | | |

[Example]

Bold mode off
0x1B 0x45 0x00

Bold mode on
0x1B 0x45 0x01






0x1B 0x47

<ESC G>

Turn double-strike mode on or off

| | | | | |
|---------------|---|-----|----|---|
| Valid for | P3 | | | |
| [Format] | Hex | 1B | 47 | n |
| | ASCII | ESC | G | n |
| [Range] | $0x00 \leq n \leq 0xFF$ | | | |
| [Description] | <p>Turns double-strike mode on or off, based on the n value:</p> <ul style="list-style-type: none">- when the Least Significant Bit (LSB) of n is 0, the double-strike mode is off.- when the Least Significant Bit (LSB) of n is 1, the double-strike mode is on. | | | |
| [Notes] | <ul style="list-style-type: none">• Only the Least Significant Bit (LSB) of n is effective.• Device output is the same in double-strike and bold mode. | | | |
| [Default] | n = 0x00 | | | |
| [Reference] | 0x1B 0x21, 0x1B 0x45 | | | |

[Example]





0x1B 0x4D

<ESC M>

Select character font

| | |
|-----------|----|
| Valid for | P3 |
|-----------|----|

| | | | | |
|----------|-------|-----|----|---|
| [Format] | Hex | 1B | 4D | n |
| | ASCII | ESC | M | n |

[Range] n = 0x00, 0x01, 0x30, 0x31

[Description] Selects characters font depending of cpi value set (Char/Inch) as follows

| CHAR/INCH | n | FUNCTION |
|------------|------------|---------------------|
| A = 11 cpi | 0x00, 0x30 | Font 11 cpi (18x24) |
| B = 15 cpi | 0x01, 0x31 | Font 15 cpi (14x24) |
| A = 15 cpi | 0x00, 0x30 | Font 15 cpi (14x24) |
| B = 20 cpi | 0x01, 0x31 | Font 20 cpi (10x24) |

[Notes]

[Default]

[Reference] [0x1B 0xC1](#)

[Example]



0x1B 0x52

<ESC R>

Select an international character set

| | | | | |
|-----------|----|--|--|--|
| Valid for | P3 | | | |
|-----------|----|--|--|--|

| | | | | |
|----------|-------|-----|----|---|
| [Format] | Hex | 1B | 52 | n |
| | ASCII | ESC | R | n |

| | |
|---------|-------------------------|
| [Range] | $0x00 \leq n \leq 0x0A$ |
|---------|-------------------------|

| | |
|---------------|---|
| [Description] | Selects the international character set n according to the table below: |
|---------------|---|

| | HEX | 23 | 24 | 40 | 5B | 5C | 5D | 5E | 60 | 7B | 7C | 7D | 7E |
|------|----------------|----|----|----|----|----|----|----|----|----|----|----|----|
| n | CHARACTER SET | | | | | | | | | | | | |
| 0x00 | U.S.A. | # | \$ | @ | [| \ |] | ^ | ` | { | | } | ~ |
| 0x01 | France | # | \$ | à | ° | ç | § | ^ | ` | é | ù | è | “ |
| 0x02 | Germany | # | \$ | § | Ä | Ö | Ü | ^ | ` | ä | ö | ü | ß |
| 0x03 | United Kingdom | £ | \$ | @ | [| \ |] | ^ | ` | { | | } | ~ |
| 0x04 | Denmark I | # | \$ | @ | Æ | Ø | Å | ^ | ` | æ | ø | å | ~ |
| 0x05 | Sweden | # | ¤ | É | Ä | Ö | Å | Ü | é | ä | ö | å | ü |
| 0x06 | Italy | # | \$ | @ | ° | \ | é | ^ | ù | à | ò | è | ì |
| 0x07 | Spain I | Pt | \$ | @ | i | Ñ | ¿ | ^ | ` | “ | ñ | } | ~ |
| 0x08 | Japan | # | \$ | @ | [| ¥ |] | ^ | ` | { | | } | ~ |
| 0x09 | Norway | # | ¤ | É | Æ | Ø | Å | Ü | é | æ | ø | å | ü |
| 0x0A | Denmark II | # | \$ | É | Æ | Ø | Å | Ü | é | æ | ø | å | ü |

[Notes]

| | |
|-----------|----------|
| [Default] | n = 0x00 |
|-----------|----------|

[Reference]

[Example]



0x1B 0x56

<ESC V>

Set 90° rotated print mode

| | | | | |
|-----------|----|--|--|--|
| Valid for | P3 | | | |
|-----------|----|--|--|--|

| | | | | |
|----------|-------|-----|----|---|
| [Format] | Hex | 1B | 56 | n |
| | ASCII | ESC | V | n |

[Range] n = 0x00, 0x01, 0x30, 0x31

[Description] Turns 90° rotation mode on or off based on the value of n as follows:

| n | FUNCTION |
|------------|---------------------------|
| 0x00, 0x30 | Disable 90° rotation mode |
| 0x01, 0x31 | Enable 90° rotation mode |

[Notes]

- When underlined mode is turned on, the device does not underline 90° rotated characters. All the same it's possible select the underline mode.
- Double-width and double-height commands in 90° rotation mode enlarge characters in the opposite directions from double-height and double-width commands in normal mode.


Default] n = 0x00

[Reference] [0x1B 0x21](#), [0x1B 0x2D](#)

[Example]

90° rotated printing off
0x1B 0x56 0x00

90° rotated printing on
0x1B 0x56 0x01





0x1B 0x74

<ESC t>

Select character code table

| | |
|-----------|----|
| Valid for | P3 |
|-----------|----|

| | | | | |
|----------|-------|-----|----|---|
| [Format] | Hex | 1B | 74 | n |
| | ASCII | ESC | t | n |

| | |
|---------|--------------------------------------|
| [Range] | $0x01 \leq n \leq 0x35$, $n = 0xFF$ |
|---------|--------------------------------------|

| | |
|---------------|---|
| [Description] | Select a page n from the character code table as follows: |
|---------------|---|

| n | PAGE |
|------|--|
| 0x00 | PC437 - U.S.A., Standard Europe |
| 0x01 | Katakana |
| 0x02 | PC850 - Multilingual |
| 0x03 | PC860 - Portuguese |
| 0x04 | PC863 - Canadian/French |
| 0x05 | PC865 - Nordic |
| 0x06 | VISCII - Vietnamese Standard Code |
| 0x0B | PC851 - Greek on request |
| 0x0C | PC853 - Turkish on request |
| 0x0D | PC857 - Turkish |
| 0x0E | PC737 - Greek |
| 0x0F | ISO8859-7 - Greek on request |
| 0x10 | WPC1252 - Scandinavian |
| 0x11 | PC866 - Cyrillic 2 |
| 0x12 | PC852 - Latin 2 |
| 0x13 | PC858 for Euro symbol in position 0xD5 |
| 0x14 | KU42 - Thai |
| 0x15 | TIS11 - Thai |
| 0x1A | TIS18 - Thai on request |
| 0x1E | TCVN_3 - Vietnamese on request |
| 0x1F | TCVN_3 - Vietnamese on request |
| 0x20 | PC720 - Arabic on request |
| 0x21 | WPC775 - Baltic Rim on request |
| 0x22 | PC855 - Cyrillic |
| 0x23 | PC861 - Icelandic on request |
| 0x24 | PC862 - Hebrew |
| 0x25 | PC864 - Arabic |
| 0x26 | PC869 - Greek on request |



| n | | PAGE |
|------|----------------------|------------|
| 0x27 | ISO8859-2 - Latin 2 | on request |
| 0x28 | ISO8859-15 - Latin 9 | on request |
| 0x29 | PC1098 - Farsi | |
| 0x2A | PC1118 - Lithuanian | on request |
| 0x2B | PC1119 - Lithuanian | on request |
| 0x2C | PC1125 - Ukrainian | |
| 0x2D | WPC1250 - Latin 2 | |
| 0x2E | WPC1251 - Cyrillic | |
| 0x2F | WPC1253 - Greek | |
| 0x30 | WPC1254 - Turkish | |
| 0x31 | WPC1255 - Hebrew | |
| 0x32 | WPC1256 - Arabic | |
| 0x33 | WPC1257 - Baltic Rim | |
| 0x34 | WPC1258 - Vietnamese | |
| 0x35 | KZ1048 - Kazakh | on request |
| 0xFF | Space page | |

[Notes]

- PC866 and PC852 tables are valid only for TrueType fonts.
- The tables are selectable only if the code pages are present on the machine. By selecting a code page not present on the machine, the code page remains the one currently in use.
- Make sure to select the font type “International” with the command **0x1C 0x25** or with the “Font type” parameter during the setup procedure (refer to the user manual of the device).

[Default]

n = 0x00

[Reference]

0x1C 0x25

[Example]

For printing Euro symbol (€), the command sequence is:
0x1B, 0x74, 0x13, 0xD5




0x1B 0x7B

<ESC {>

Turn upside-down printing mode on or off

| | | | | |
|---------------|---|-----|----|---|
| Valid for | P3 | | | |
| [Format] | Hex | 1B | 7B | n |
| | ASCII | ESC | { | n |
| [Range] | 0x00 ≤ n ≤ 0xFF | | | |
| [Description] | <p>Turns upside-down printing mode on or off, based on the value of n:</p> <ul style="list-style-type: none">- when the Least Significant Bit (LSB) of n is 0, the upside-down printing mode is off.- when the Least Significant Bit (LSB) of n is 1, the upside-down printing mode is on. | | | |
| [Notes] | <ul style="list-style-type: none">• Only the Least Significant Bit (LSB) of n is effective.• This command is valid only if entered at the beginning of a line.• In upside-down printing mode, the device rotates the line to be printed 180° and then prints it. | | | |
| [Default] | n = 0x00 | | | |
| [Reference] | | | | |

[Example]





0x1B 0xC1

Select character pitch

| | | | | |
|-----------|----|--|--|--|
| Valid for | P3 | | | |
|-----------|----|--|--|--|

| | | | | |
|----------|-------|-----|------|---|
| [Format] | Hex | 1B | C1 | n |
| | ASCII | ESC | 0xC1 | n |

| | |
|---------|----------------|
| [Range] | n = 0x00, 0x01 |
| | n = 0x30, 0x31 |

| | |
|---------------|--|
| [Description] | This command selects the character pitch expressed in cpi (characters per inch) based on the values of n as follows: |
|---------------|--|


| n | PITCH | |
|------------|-----------------|-----------------|
| 0x00, 0x30 | Font A = 11 cpi | Font B = 15 cpi |
| 0x01, 0x31 | Font A = 15 cpi | Font B = 20 cpi |

[Notes]

| | |
|-----------|----------|
| [Default] | n = 0x00 |
|-----------|----------|

| | |
|-------------|-----------|
| [Reference] | 0x1B 0x21 |
|-------------|-----------|

[Example]





0x1C 0x25

<FS %>

Select the font type

| | | | | | | | | | | | | |
|---------------|--|----|----|---|---|-----------|------|---------------|------|-----------------|------|--------------|
| Valid for | P3 | | | | | | | | | | | |
| [Format] | Hex | 1C | 25 | n | | | | | | | | |
| | ASCII | FS | % | n | | | | | | | | |
| [Range] | n = 0x00, 0x01 | | | | | | | | | | | |
| [Description] | Select the font type based on the value of n as follows: | | | | | | | | | | | |
| | <table><tr><td>n</td><td>FONT TYPE</td></tr><tr><td>0x00</td><td>International</td></tr><tr><td>0x01</td><td>Chinese GB18030</td></tr><tr><td>0x02</td><td>Korean CP949</td></tr></table> | | | | n | FONT TYPE | 0x00 | International | 0x01 | Chinese GB18030 | 0x02 | Korean CP949 |
| n | FONT TYPE | | | | | | | | | | | |
| 0x00 | International | | | | | | | | | | | |
| 0x01 | Chinese GB18030 | | | | | | | | | | | |
| 0x02 | Korean CP949 | | | | | | | | | | | |
| [Notes] | <ul style="list-style-type: none">• The selection made by this command is stored in the RAM memory. Turning off the device reverts to the default value, that can be set with the “Font type” parameter during the setup procedure (refer to the user manual of the device).• After selecting the font type “International” it must be selected the desired character code table using the command 0x1B 0x74. | | | | | | | | | | | |
| [Default] | n = 0x00 | | | | | | | | | | | |
| [Reference] | 0x1B 0x74, see the Chinese fonts management commands manual. | | | | | | | | | | | |
| [Example] | | | | | | | | | | | | |



0x1D 0x21

<GS !>

Select character size

| Valid for | P3 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
|---------------|---|----------|--|--------|----|------------|----|----------------|----|----------------|----|----------------|----|----------------|----|----------------|----|----------------|----|----------------|--|--|-----|--------|----|------------|----|-----------------|----|-----------------|----|-----------------|----|-----------------|----|-----------------|----|-----------------|----|-----------------|
| [Format] | Hex ASCII | 1D GS | 21 ! | n n | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| [Range] | 0x00 ≤ n ≤ 0x07 0x20 ≤ n ≤ 0x27 0x40 ≤ n ≤ 0x47 0x60 ≤ n ≤ 0x67 | | 0x10 ≤ n ≤ 0x17 0x30 ≤ n ≤ 0x37 0x50 ≤ n ≤ 0x57 0x70 ≤ n ≤ 0x77 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| [Description] | <p>Selects character height and width, as follows:</p> <ul style="list-style-type: none">• Bits 0 to 3: to select character height (see table 2).• Bits 4 to 7: to select character width (see table 1). | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| | <table><caption>Table 1 Select character width</caption><thead><tr><th>HEX</th><th>WIDTH</th></tr></thead><tbody><tr><td>00</td><td>1 (normal)</td></tr><tr><td>10</td><td>2 (width = 2x)</td></tr><tr><td>20</td><td>3 (width = 3x)</td></tr><tr><td>30</td><td>4 (width = 4x)</td></tr><tr><td>40</td><td>5 (width = 5x)</td></tr><tr><td>50</td><td>6 (width = 6x)</td></tr><tr><td>60</td><td>7 (width = 7x)</td></tr><tr><td>70</td><td>8 (width = 8x)</td></tr></tbody></table> | | HEX | WIDTH | 00 | 1 (normal) | 10 | 2 (width = 2x) | 20 | 3 (width = 3x) | 30 | 4 (width = 4x) | 40 | 5 (width = 5x) | 50 | 6 (width = 6x) | 60 | 7 (width = 7x) | 70 | 8 (width = 8x) | <table><caption>Table 2 Select character height</caption><thead><tr><th>HEX</th><th>HEIGHT</th></tr></thead><tbody><tr><td>00</td><td>1 (normal)</td></tr><tr><td>01</td><td>2 (height = 2x)</td></tr><tr><td>02</td><td>3 (height = 3x)</td></tr><tr><td>03</td><td>4 (height = 4x)</td></tr><tr><td>04</td><td>5 (height = 5x)</td></tr><tr><td>05</td><td>6 (height = 6x)</td></tr><tr><td>06</td><td>7 (height = 7x)</td></tr><tr><td>07</td><td>8 (height = 8x)</td></tr></tbody></table> | | HEX | HEIGHT | 00 | 1 (normal) | 01 | 2 (height = 2x) | 02 | 3 (height = 3x) | 03 | 4 (height = 4x) | 04 | 5 (height = 5x) | 05 | 6 (height = 6x) | 06 | 7 (height = 7x) | 07 | 8 (height = 8x) |
| HEX | WIDTH | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 00 | 1 (normal) | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 10 | 2 (width = 2x) | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 20 | 3 (width = 3x) | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 30 | 4 (width = 4x) | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 40 | 5 (width = 5x) | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 50 | 6 (width = 6x) | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 60 | 7 (width = 7x) | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 70 | 8 (width = 8x) | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| HEX | HEIGHT | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 00 | 1 (normal) | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 01 | 2 (height = 2x) | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 02 | 3 (height = 3x) | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 03 | 4 (height = 4x) | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 04 | 5 (height = 5x) | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 05 | 6 (height = 6x) | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 06 | 7 (height = 7x) | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 07 | 8 (height = 8x) | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| [Notes] | <ul style="list-style-type: none">• This command is effective for all characters (except HRI characters).• If n falls outside the defined range, this command is ignored.• Characters enlarged to different heights on the same line are aligned at the baseline or top line.• 0x1B 0x21 can also be used to select character size. However, the setting of the last received command is the effective one.• This command is effective on the x and y axes. In case of 90°/270° rotated characters, bit from 0 to 3 select character width and bit from 4 to 7 select character height. | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| [Default] | n = 0x00 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| [Reference] | 0x1B 0x21 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| [Example] | For printing a character with 6x width and height the command sequence is: 0x1D 0x21 0x55 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |



0x1D 0x42


<GS B>

Turn black and white reverse printing mode on or off

| | | | | |
|---------------|---|----|----|---|
| Valid for | P3 | | | |
| [Format] | Hex | 1D | 42 | n |
| | ASCII | GS | B | n |
| [Range] | 0x00 ≤ n ≤ 0xFF | | | |
| [Description] | <p>Turns black and white reverse printing mode on or off, based on the value of n:</p> <ul style="list-style-type: none">- when the Least Significant Bit (LSB) of n is 0, white/black reverse printing is turned off.- when the Least Significant Bit (LSB) of n is 1, white/black reverse printing is turned on. | | | |
| [Notes] | <ul style="list-style-type: none">• Only the Least Significant Bit (LSB) of n is effective.• This command is available for both built-in and user-defined characters.• This command does not affect bit image, downloaded bit image, barcode, HRI characters and spacing skipped by 0x09, 0x1B 0x24 and 0x1B 0x5C.• This command does not affect white space between lines.• White/black reverse mode has a higher priority than underline mode. Even if underline mode is on, it will be disabled (but not cancelled) when black and white reverse mode is selected. | | | |
| [Default] | n = 0x00 | | | |

[Reference]

[Example]





LINE SPACING COMMANDS

0x1B 0x30

<ESC 0>

Select 1/8-inch line spacing

| | | | |
|--------------------------------|-------|-----|----|
| Valid for | P3 | | |
| [Format] | Hex | 1B | 30 |
| | ASCII | ESC | 0 |
| [Range] | | | |
| [Description] | | | |
| Selects 1/8-inch line spacing. | | | |
| [Notes] | | | |
| [Default] | | | |
| [Reference] | | | |
| 0x1B 0x32, 0x1B 0x33 | | | |
| [Example] | | | |





0x1B 0x32

<ESC 2>

Select 1/6-inch line spacing

| | |
|-----------|----|
| Valid for | P3 |
|-----------|----|

| | | | |
|----------|-------|-----|----|
| [Format] | Hex | 1B | 32 |
| | ASCII | ESC | 2 |

[Range]


[Description] Selects 1/6-inch line spacing.

[Notes]

[Default]

[Reference] 0x1B 0x30, 0x1B 0x33

[Example]





0x1B 0x33

<ESC 3>

Set line spacing

| | | | | |
|---------------|--|-----|----|---|
| Valid for | P3 | | | |
| [Format] | Hex | 1B | 33 | n |
| | ASCII | ESC | 3 | n |
| [Range] | $0x00 \leq n \leq 0xFF$ | | | |
| [Description] | Sets line spacing to $[n \times (\text{vertical or horizontal motion unit})]$. | | | |
| [Notes] | <ul style="list-style-type: none">• The horizontal and vertical motion unit are specified by 0x1D 0x50. Changing the horizontal or vertical motion unit does not affect the current line spacing.• The 0x1D 0x50 command can change the horizontal (and vertical) motion unit. However, the value cannot be less than the minimum vertical movement amount.• In standard mode, the vertical motion unit is used.• The maximum spacing is 32.5 mm. | | | |
| [Default] | n = 0x40 (1/6 inch) | | | |
| [Reference] | 0x1B 0x30 , 0x1B 0x32 , 0x1D 0x50 | | | |
| [Example] | | | | |



PRINT COMMANDS

0x0A

<LF>

Print and line feed

| | | |
|-----------|----|--|
| Valid for | P3 | |
|-----------|----|--|

| | | |
|----------|-------|----|
| [Format] | Hex | 0A |
| | ASCII | LF |

[Range]


[Description] This command sets the print position to the beginning of the line printing the data in the buffer and feeding one line based on the line spacing set with the command 0x1B 0x30 or 0x1B 0x32.

[Notes] If the buffer is empty, the printing feeds of a value equal to the sum of the character height and line spacing.

[Default] 1/6-inch (32 dots)

[Reference] 0x1B 0x30, 0x1B 0x32, 0x1B 0x33, 0x0D

[Example]




To print the ticket shown in figure the command sequence is:
ABCDEFGH 0x0A 123456 0x0A

0x0D

<CR>

Print and carriage return

| | | |
|---------------|---|----|
| Valid for | P3 | |
| [Format] | Hex | 0D |
| | ASCII | CR |
| [Range] | | |
| [Description] | This command handles the end of a line text. | |
| [Notes] | If “Autofeed” setup parameter is set to “CR enabled”, this command works in the same way as 0x0A , otherwise it is disregarded. | |
| [Default] | See “Autofeed” setup parameter (refer to the user manual of the device). | |
| [Reference] | 0x0A | |
| [Example] | | |



To print the ticket shown in figure the command sequence is:
 ABCDEFGH 0x0D 123456 0x0D



0x1B 0x4A

<ESC J>

Print and paper feed

| | | | | |
|---------------|--|-----|----|---|
| Valid for | P3 | | | |
| [Format] | Hex | 1B | 4A | n |
| | ASCII | ESC | J | n |
| [Range] | 0x00 ≤ n ≤ 0xFF | | | |
| [Description] | Prints the data saved in the print buffer and feeds the paper [n × vertical or horizontal motion unit]. | | | |
| [Notes] | <ul style="list-style-type: none">• After printing has been completed, this command sets the print starting position to the beginning of the line.• The paper feed amount set by this command does not affect the values set by 0x1B 0x30 or 0x1B 0x32.• The horizontal and vertical motion units are specified by 0x1D 0x50.• 0x1D 0x50 can change the vertical (and horizontal) motion unit. However, the value cannot be less than the minimum vertical movement amount.• In standard mode, the vertical motion unit is used. | | | |
| [Default] | | | | |
| [Reference] | 0x1D 0x50 | | | |
| [Example] | | | | |



0x1B 0x64

<ESC d>

Print and feed paper n lines

| | | | | |
|---------------|--|-----|----|---|
| Valid for | P3 | | | |
| [Format] | Hex | 1B | 64 | n |
| | ASCII | ESC | d | n |
| [Range] | $0x00 \leq n \leq 0xFF$ | | | |
| [Description] | Prints the data saved in the print buffer and feeds the paper n lines. | | | |
| [Notes] | <ul style="list-style-type: none">• n rows paper feed is equivalent to (n × char height + line spacing set).• Sets the print starting position at the beginning of the line.• This command does not affect the line spacing set by 0x1B 0x32 or 0x1B 0x33.• The maximum paper feed amount is 254 lines. Even if a paper feed amount of more than 254 lines is set, the device feeds the paper only 254 lines. | | | |
| [Default] | | | | |
| [Reference] | 0x1B 0x32 , 0x1B 0x33 | | | |
| [Example] | | | | |



0x1D 0x7C

<GS |>

Set printing density

| | | | | |
|-----------|----|--|--|--|
| Valid for | P3 | | | |
|-----------|----|--|--|--|

| | | | | |
|----------|-------|----|----|---|
| [Format] | Hex | 1D | 7C | n |
| | ASCII | GS | | n |

| | |
|---------|-------------------------|
| [Range] | $0x02 \leq n \leq 0x06$ |
| | $0x32 \leq n \leq 0x36$ |

[Description] Sets printing density. n specifies printing density as follows:


| n | PRINTING DENSITY |
|------------|------------------|
| 0x02, 0x32 | - 25% |
| 0x03, 0x33 | - 12.5% |
| 0x04, 0x34 | 0% |
| 0x05, 0x35 | + 12.5% |
| 0x06, 0x36 | + 25% |

[Notes] Printing density reverts to the default value when the device is reset or turned off.

[Default] n = 0x04

[Reference]

[Example]





STATUS COMMANDS

0x10 0x04

<DLE EOT>

Real-time status transmission

| | | | | |
|---------------|--|-----|-----|---|
| Valid for | P3 | | | |
| [Format] | Hex | 10 | 04 | n |
| | ASCII | DLE | EOT | n |
| [Range] | 0x01 ≤ n ≤ 0x04 n = 0x11, 0x14, 0x15 | | | |
| [Description] | Transmits the selected status when this command is received. The status to be transmitted is indicated in the following table: | | | |

| | |
|----------|------------------------------------|
| n = 0x01 | transmits device status |
| n = 0x02 | transmits off-line status |
| n = 0x03 | transmits error status |
| n = 0x04 | transmits paper roll sensor status |
| n = 0x11 | transmits print status |
| n = 0x14 | transmits full status |
| n = 0x15 | transmits device ID |

Device status (n = 0x01)

| BIT | OFF/ON | HEX | FUNCTION |
|-----|--------|-----|------------------------|
| 0 | Off | 00 | Not used. Fixed to off |
| 1 | On | 02 | Not used. Fixed to on |
| 2 | - | - | RESERVED |
| 3 | Off | 00 | On-line |
| | On | 08 | Off-line |
| 4 | On | 10 | Not used. Fixed to on |
| 5 | - | - | RESERVED |
| 6 | - | - | RESERVED |
| 7 | Off | 00 | FEED key released |
| | On | 80 | FEED key pressed |



Off-line status (n = 0x02)

| BIT | OFF/ON | HEX | FUNCTION |
|-----|--------|-----|--------------------------------|
| 0 | Off | 00 | Not used. Fixed to off |
| 1 | On | 02 | Not used. Fixed to on |
| 2 | Off | 00 | Cover closed |
| | On | 04 | Cover opened |
| 3 | Off | 00 | Paper isn't fed by FEED key |
| | On | 08 | Paper is fed by FEED key |
| 4 | On | 10 | Not used. Fixed to on |
| 5 | Off | 00 | Paper present |
| | On | 20 | Printing stop due to paper end |
| 6 | Off | 00 | No error |
| | On | 40 | Error |
| 7 | Off | 00 | Not used. Fixed to off |

Error status (n = 0x03)

| BIT | OFF/ON | HEX | FUNCTION |
|-----|--------|-----|---------------------------|
| 0 | Off | 00 | Not used. Fixed to off |
| 1 | On | 02 | Not used. Fixed to on |
| 2 | - | - | RESERVED |
| 3 | Off | 00 | Autocutter ok |
| | On | 08 | Autocutter error |
| 4 | On | 10 | Not used. Fixed to on |
| 5 | Off | 00 | No unrecoverable error |
| | On | 20 | Unrecoverable error |
| 6 | Off | 00 | No auto-recoverable error |
| | On | 40 | Auto-recoverable error |
| 7 | Off | 00 | Not used. Fixed to off |



Paper roll sensor status (n = 0x04)

| BIT | OFF/ON | HEX | FUNCTION |
|------|--------|-----|------------------------|
| 0 | Off | 00 | Not used. Fixed to off |
| 1 | On | 02 | Not used. Fixed to on |
| 2, 3 | Off | 00 | Paper present |
| | On | 0C | Low paper |
| 4 | On | 10 | Not used. Fixed to on |
| 5, 6 | Off | 00 | Paper present |
| | On | 60 | Paper not present |
| 7 | Off | 00 | Not used. Fixed to off |

Print status (n = 0x11)

| BIT | OFF/ON | HEX | FUNCTION |
|-----|--------|-----|------------------------------------|
| 0 | Off | 00 | Not used. Fixed to off |
| 1 | On | 02 | Not used. Fixed to on |
| 2 | Off | 00 | Paper drag motor off |
| | On | 04 | Paper drag motor on |
| 3 | - | - | RESERVED |
| 4 | On | 10 | Not used. Fixed to on |
| 5 | Off | 00 | Paper present |
| | On | 20 | Printing stopped out for paper end |
| 6 | - | - | RESERVED |
| 7 | Off | 00 | Not used. Fixed to off |

Full status (n = 0x14, 6 bytes)

1st byte = 0x10 (DLE)

2nd byte = 0x0F



3rd byte = Paper status

| BIT | OFF/ON | HEX | FUNCTION |
|-----|--------|-----|-------------------|
| 0 | Off | 00 | Paper present |
| | On | 01 | Paper not present |
| 1 | - | - | RESERVED |
| 2 | - | - | RESERVED |
| 3 | - | - | RESERVED |
| 4 | - | - | RESERVED |
| 5 | - | - | RESERVED |
| 6 | - | - | RESERVED |
| 7 | - | - | RESERVED |

4th byte = User status

| BIT | OFF/ON | HEX | FUNCTION |
|-----|--------|-----|------------------------------|
| 0 | Off | 00 | No error, printing head down |
| | On | 01 | Printing head up error |
| 1 | Off | 00 | Cover closed |
| | On | 02 | Cover opened |
| 2 | Off | 00 | No spooling |
| | On | 04 | Spooling |
| 3 | Off | 00 | Drag paper motor off |
| | On | 08 | Drag paper motor on |
| 4 | - | - | RESERVED |
| 5 | Off | 00 | LF key released |
| | On | 20 | LF key pressed |
| 6 | - | - | RESERVED |
| 7 | - | - | RESERVED |



5th byte = Recoverable status error

| BIT | OFF/ON | HEX | FUNCTION |
|-----|--------|-----|----------------------------|
| 0 | Off | 00 | Head temperature ok |
| | On | 01 | Head temperature error |
| 1 | - | - | RESERVED |
| 2 | Off | 00 | No COM error |
| | On | 04 | RS232 COM error |
| 3 | Off | 00 | Power supply voltage ok |
| | On | 08 | Power supply voltage error |
| 4 | - | - | RESERVED |
| 5 | Off | 00 | Command ok |
| | On | 20 | Command error |
| 6 | - | - | RESERVED |
| 7 | Off | 00 | Black mark search ok |
| | On | 80 | Error in black mark search |

6th byte = Unrecoverable error status

| BIT | OFF/ON | HEX | FUNCTION |
|-----|--------|-----|------------------|
| 0 | Off | 00 | Autocutter ok |
| | On | 01 | Autocutter error |
| 1 | - | - | RESERVED |
| 2 | - | - | RESERVED |
| 3 | Off | 00 | EEPROM ok |
| | On | 08 | EEPROM error |
| 4 | - | - | RESERVED |
| 5 | - | - | RESERVED |
| 6 | - | - | RESERVED |
| 7 | - | - | RESERVED |



Transmit device ID (n = 0x15)

1st byte = (refer to command [0x1D 0x49](#))

[Notes] This command is immediately executed even when the data buffer is full.

[Default]

[Reference]

[Example] Request for device status transmission:
0x10 0x04 0x01
Device response:
0x80 FEED key pressed



0x1C 0xEA

Transmit the device serial number

| | | | | |
|---------------|--|----|------|---|
| Valid for | P3 | | | |
| [Format] | Hex | 1C | EA | n |
| | ASCII | FS | 0xEA | n |
| [Range] | n = 0x52, 0x72 | | | |
| [Description] | Transmits the device serial number. | | | |
| [Notes] | <ul style="list-style-type: none">• The serial number is a string of 16 alphanumeric characters.• If the printer serial number is not defined, the device returns a string of 16 characters with a value of 0x00. | | | |
| [Default] | | | | |
| [Reference] | | | | |
| [Example] | To read the device serial number the command sequence is: 0x1C 0xEA 0x52 | | | |
| | The device returns a string of 16 alphanumeric characters just like the following: 'ABC0123456789012' | | | |



0x1D 0x72

<GS r>

Transmit status

| | |
|-----------|----|
| Valid for | P3 |
|-----------|----|

| | | | | |
|----------|-------|----|----|---|
| [Format] | Hex | 1D | 72 | n |
| | ASCII | GS | r | n |

| | |
|---------|-----------------|
| [Range] | 0x01 ≤ n ≤ 0x02 |
| | 0x31 ≤ n ≤ 0x32 |

| | |
|---------------|---|
| [Description] | Transmits the status specified by n as follows: |
|---------------|---|

| n | FUNCTION |
|------------|-----------------------------------|
| 0x01, 0x31 | Transmits paper sensor status |
| 0x02, 0x32 | Transmits drawer connector status |

Paper sensor status (n = 0x01, 0x31)

| BIT | OFF/ON | HEX | FUNCTION |
|-----|--------|-----|--|
| 0,1 | Off | 00 | Not used. Fixed to Off |
| 2,3 | Off | 00 | Paper presence sensor: paper present |
| | On | 0C | Paper presence sensor: paper not present |
| 4 | Off | 00 | Not used. Fixed to Off |
| 5 | - | - | Undefined |
| 6 | - | - | Undefined |
| 7 | Off | 00 | Not used. Fixed to Off |

Drawer connector status (n = 0x02, 0x32)

| BIT | OFF/ON | HEX | FUNCTION |
|-----|--------|-----|------------------------|
| 0 | Off | 00 | Pin 3 at low level |
| | On | 01 | Pin 3 at high level |
| 1 | - | - | Undefined |
| 2 | - | - | Undefined |
| 3 | - | - | Undefined |
| 4 | Off | 00 | Not used. Fixed to Off |
| 5 | - | - | Undefined |
| 6 | - | - | Undefined |
| 7 | Off | 00 | Not used. Fixed to Off |



| | |
|-------------|--|
| [Notes] | This command is executed when the data is processed in the data buffer. Therefore, there may be a time lag between receiving the command and transmitting the status, depending on data buffer status. |
| [Default] | |
| [Reference] | 0x10 0x04 |
| [Example] | |



0x1D 0xE0

Enable or disable automatic FULL STATUS BACK

| | | | | |
|-----------|----|--|--|--|
| Valid for | P3 | | | |
|-----------|----|--|--|--|

| | | | | |
|----------|-------|----|------|---|
| [Format] | Hex | 1D | E0 | n |
| | ASCII | GS | 0xE0 | n |

| | |
|---------|-------------------------|
| [Range] | $0x00 \leq n \leq 0xFF$ |
|---------|-------------------------|

| | |
|---------------|--|
| [Description] | Enable or disable automatic full status back. n specifies the composition of full status as follows: |
|---------------|--|

| BIT | OFF/ON | HEX | FUNCTION |
|-----|--------|-----|------------------------------------|
| 0 | Off | 00 | Disable paper status |
| | On | 01 | Enable paper status |
| 1 | Off | 00 | Disable user status |
| | On | 02 | Enable user status |
| 2 | Off | 00 | Disable recoverable error status |
| | On | 04 | Enable recoverable error status |
| 3 | Off | 00 | Disable unrecoverable error status |
| | On | 08 | Enable unrecoverable error status |
| 4 | - | - | Undefined |
| 5 | - | - | Undefined |
| 6 | - | - | Undefined |
| 7 | - | - | Undefined |

| | |
|---------|---|
| [Notes] | Once enable at least one byte of the full status, for each change of at least one of the bits which compose the required status, the status sent in automatic from the device will be so composed as follows: |
|---------|---|

1st Byte = 0x10 (DLE=

2nd Byte = n

| |
|-----------|
| [Default] |
|-----------|

| | |
|-------------|-----------|
| [Reference] | 0x10 0x04 |
|-------------|-----------|

| |
|-----------|
| [Example] |
|-----------|



0x1D 0xE1

Reading of length paper available before virtual paper-end

| | | | |
|---------------|---|----|------|
| Valid for | P3 | | |
| [Format] | Hex | 1D | E1 |
| | ASCII | GS | 0xE1 |
| [Range] | | | |
| [Description] | Reading of length paper available before virtual paper-end (expressed in centimetres). The command return a string pointing out how much paper is available. | | |
| [Notes] | <ul style="list-style-type: none">• The length of residual paper reported is just as an indication because tolerances and other factors are not taken into consideration (paper thickness, roll core diameter, roll core thickness).• The virtual paper-end limit is set by the command 0x1D 0xE6.• To set virtual paper-end limit, measure the length of the paper from low paper to the end of the roll, using several of them. | | |
| [Default] | | | |
| [Reference] | 0x1D 0xE6 | | |
| [Example] | If there are 5.1 m before paper end, the answer will be: '510cm' | | |



0x1D 0xE2

Reading number of cuts performed by the autocutter

| | | | |
|---------------|--|----|------|
| Valid for | P3 | | |
| [Format] | Hex | 1D | E2 |
| | ASCII | GS | 0xE2 |
| [Range] | | | |
| [Description] | Reading the number of cuts performed by the autocutter. | | |
| [Notes] | The command returns a string indicating how many cuts are performed by the autocutter. | | |
| [Default] | | | |
| [Reference] | | | |
| [Example] | If the autocutter has performed 785 cuts, the answer will be: '785cuts' | | |



0x1D 0xE3

Reading of length of printed paper

| | | | |
|---------------|---|----|------|
| Valid for | P3 | | |
| [Format] | Hex | 1D | E3 |
| | ASCII | GS | 0xE3 |
| [Range] | | | |
| [Description] | Reading of length expressed in centimetre of printed paper. | | |
| [Notes] | The command returns a string indicating how much paper is printed. | | |
| [Default] | | | |
| [Reference] | | | |
| [Example] | If the device has printed about 388.9 m, the answer will be: '38890cm' | | |



0x1D 0xE5

Reading number of power up

| | | | |
|---------------|---|----|------|
| Valid for | P3 | | |
| [Format] | Hex | 1D | E5 |
| | ASCII | GS | 0xE5 |
| [Range] | | | |
| [Description] | Reading number of power up of the device. | | |
| [Notes] | The command returns a string indicating the number of device power ups. | | |
| [Default] | | | |
| [Reference] | | | |
| [Example] | If the device is turned on 512 times, the answer will be: '512on' | | |



BIT-IMAGE COMMANDS

0x1B 0x2A

<ESC *>

Select bit image mode

| | |
|-----------|----|
| Valid for | P3 |
|-----------|----|

| | | | | | | | |
|----------|-------|-----|----|---|----|----|---------|
| [Format] | Hex | 1B | 2A | m | nL | nH | d1...dk |
| | ASCII | ESC | * | m | nL | nH | d1...dk |

| | |
|---------|---|
| [Range] | m = 0x00, 0x01, 0x20, 0x21 0x00 ≤ nL ≤ 0xFF 0x00 ≤ nH ≤ 0x03 0x00 ≤ d ≤ 0xFF |
|---------|---|


[Description] Selects a bit image mode using m for the number of dots specified by nL and nH, as follows:

| m | MODE | VERTICAL DIRECTION | | HORIZONTAL DIRECTION | |
|------|------------------------|--------------------|-----|----------------------|---------------------|
| | | N. DOTS | DPI | DPI | N. DATA (k) |
| 0x00 | 8 dots single density | 8 | 67 | 100 | nL + nH × 256 |
| 0x01 | 8 dots double density | 8 | 67 | 200 | nL + nH × 256 |
| 0x20 | 24 dots single density | 24 | 200 | 100 | (nL + nH × 256) × 3 |
| 0x21 | 24 dots double density | 24 | 200 | 200 | (nL + nH × 256) × 3 |


- [Notes]
- The nL and nH commands indicate the number of dots of the bit image in the horizontal direction. The number of dots is calculated using: nL + nH × 256.
 - If the bit image data input exceeds the number of dots to be printed on a line, the excess data is ignored.
 - d indicates the bit image data. Set a corresponding bit to 1 to print a dot, or to 0 to not print the dot.
 - If the value of m is outside the specified range, nL and data following it are processed as normal data.
 - If the width of the printing area set by 0x1D 0x4C and 0x1D 0x57 is less than the width required by the data set using 0x1B 0x2A, the excess data are ignored.
 - To print the bit image use 0x0A, 0x0D, 0x1B 0x4A or 0x1B 0x64.
 - After printing a bit image, the device returns to normal data processing mode.
 - This command is not affected by the bold, double-strike, underline (etc.) print modes, except for the upside-down mode.

- The relationship between the image data and the dots to be printed is as follows:

8-dot bit image




24-dot bit image



[Default]


[Reference]

[Example]




8 dots

8 dots single density




8 dots

8 dots double density



24 dots

24 dots single density



24 dots

24 dots double density



0x1D 0x2A


<GS *>

Define received bit image

| | | | | | | |
|---------------|--|----|----|---|---|-------------------|
| Valid for | P3 | | | | | |
| [Format] | Hex | 1D | 2A | x | y | d1...d(x × y × 8) |
| | ASCII | GS | * | x | y | d1...d(x × y × 8) |
| [Range] | 0x01 ≤ x ≤ 0xFF 0x01 ≤ y ≤ 0x30 x × y ≤ 1536 0x00 ≤ d ≤ 0xFF | | | | | |
| [Description] | Defines a received bit image using the number of dots specified by x and y. <ul style="list-style-type: none">• x specifies the number of bytes in the horizontal direction.• y specifies the number of bytes in the vertical direction. | | | | | |
| [Notes] | <ul style="list-style-type: none">• The number of bytes in horizontal and vertical directions (x and y) are the horizontal and vertical size of the starting image divided by 8.• If x × y is out of the specified range, this command is disabled.• The d indicates bit-image data. Data (d) specifies a bit printed to 1 and not printed to 0.• The received bit image definition is cleared when:<ul style="list-style-type: none">- 0x1B 0x40 is executed.- 0x1B 0x26 is executed.- Device is reset or the power is turned off.• The image is saved in the graphic memory of the device. | | | | | |
| [Default] | | | | | | |
| [Reference] | | | | | | |

[Example]

The following figure shows the relationship between the received bit image and the printed data.





0x1D 0x2F

<GS />

Print received bit image

| Valid for | P3 | | | | | | | | | | | | | |
|---|---|----------|---------|--------|---|------|------------|--------|------------|--------------|------------|---------------|------------|-----------|
| [Format] | Hex ASCII | 1D GS | 2F / | m m | | | | | | | | | | |
| [Range] | 0x00 ≤ m ≤ 0x03 0x30 ≤ m ≤ 0x33 | | | | | | | | | | | | | |
| [Description] | Prints a received bit image using the mode specified by m as follows: | | | | | | | | | | | | | |
| <table><tr><th>m</th><th>MODE</th></tr><tr><td>0x00, 0x30</td><td>Normal</td></tr><tr><td>0x01, 0x31</td><td>Double width</td></tr><tr><td>0x02, 0x32</td><td>Double height</td></tr><tr><td>0x03, 0x33</td><td>Quadruple</td></tr></table> | | | | | m | MODE | 0x00, 0x30 | Normal | 0x01, 0x31 | Double width | 0x02, 0x32 | Double height | 0x03, 0x33 | Quadruple |
| m | MODE | | | | | | | | | | | | | |
| 0x00, 0x30 | Normal | | | | | | | | | | | | | |
| 0x01, 0x31 | Double width | | | | | | | | | | | | | |
| 0x02, 0x32 | Double height | | | | | | | | | | | | | |
| 0x03, 0x33 | Quadruple | | | | | | | | | | | | | |
| [Notes] | <ul style="list-style-type: none">• This command is ignored if a received bit image has not been defined.• In standard mode, this command is effective only when there is no data in the print buffer.• This command has no effect in the print modes bold, underline, character size, or white/black reverse printing), except for upside-down printing mode (180° rotation).• If the received bit-image to be printed exceeds the printable area, the excess data is not printed.• If the printing area width set by 0x1D 0x4C and 0x1D 0x57 is less than one line in vertical, the following processing is performed only on the line in question:<ol style="list-style-type: none">1) The printing area width is extended to the right up to one line in vertical. In this case, printing does not exceed the printable area.2) If the printing area width cannot be extended by one line in vertical, the left margin is reduced to accommodate one line in vertical. | | | | | | | | | | | | | |
| [Default] | | | | | | | | | | | | | | |
| [Reference] | 0x1D 0x2A | | | | | | | | | | | | | |
| [Example] | | | | | | | | | | | | | | |



0x1D 0x76 0x30

<GS v 0>

Print raster bit image

| | |
|-----------|----|
| Valid for | P3 |
|-----------|----|

| | | | | | | |
|----------|-------|----|----|----|---|---------------------|
| [Format] | Hex | 1D | 76 | 30 | m | xL xH yL yH d1...dk |
| | ASCII | GS | v | 0 | m | xL xH yL yH d1...dk |

| | |
|---------|---|
| [Range] | $0x00 \leq m \leq 0x03$, $0x30 \leq m \leq 0x31$ $0x00 \leq xL \leq 0xFF$ $0x00 \leq xH \leq 0xFF$ ($1 \leq xL + xH \times 256 \leq 65535$) $0x00 \leq yL \leq 0xFF$ $0x00 \leq yH \leq 0x08$ ($1 \leq yL + yH \times 256 \leq 2047$) $0x00 \leq d \leq 0xFF$ $k = (xL + xH \times 256) + (yL + yH \times 256)$ (except for $k = 0$) |
|---------|---|

| | |
|---------------|--|
| [Description] | Selects raster bit image mode. The value of m selects the mode as follows: |
|---------------|--|

| m | MODE |
|------------|---------------|
| 0x00, 0x30 | Normal |
| 0x01, 0x31 | Double width |
| 0x02, 0x32 | Double height |
| 0x03, 0x33 | Quadruple |

- xL, xH selects the number of data bytes ($xL + xH \times 256$) in the horizontal direction for the bit image.
- yL, yH selects the number of data bytes ($yL + yH \times 256$) in the vertical direction for the bit image.
- k shows the number of data of the image. It's an explanation parameter so it isn't necessary to transmit it.
- d shows the data of the image.

| | |
|---------|--|
| [Notes] | <ul style="list-style-type: none"> • In standard mode for receipt paper, this command is effective only when there is no data in the print buffer. • The data (d) identify as 1 a printed bit and as 0 a non printed bit. • If a raster bit image is longer than one line, the surplus data aren't printed. • This command has no effect in all print modes (character size, bold, upside-down, underline, white/black reverse printing, etc.) for raster bit image, except the reverse mode (90° anticlockwise rotation). • This command feed the paper as much as is necessary to print the raster bit image, though the spacing set by 0x1B 0x32 or 0x1B 0x33. |
|---------|--|



- Don't use this command during a macro execution because it can't be included in a macro.
- After the printing, the printing position moves to the beginning of the line.
- The following table shows the relationship between the downloaded bit image and the printed data:

| | | | |
|------|------|------|--------|
| d1 | d2 | ... | dx |
| dX+1 | dX+2 | ... | dX x 2 |
| : | : | ... | : |
| ... | dk-2 | dk-1 | d |

[Default]

[Reference]

[Example]



LOGOS MANAGEMENT COMMANDS

0x1C 0x70

<FS p>

Print logo

| | |
|-----------|----|
| Valid for | P3 |
|-----------|----|

| | | | | | |
|----------|-------|----|----|---|---|
| [Format] | Hex | 1C | 70 | m | n |
| | ASCII | FS | p | m | n |

| | |
|---------|---|
| [Range] | 0x00 ≤ m ≤ 0x03 (Logo number) n = 0x00, 0x01, 0x02, 0x03 |
|---------|---|

| | |
|---------------|---|
| [Description] | The bit image specified by m (if stored in flash memory) is printed in the mode indicated by n as described in the following table: |
|---------------|---|


| n | PRINT MODE |
|------|--------------------------------|
| 0x00 | Normal |
| 0x01 | Double width |
| 0x02 | Double height |
| 0x03 | Double width and double height |

[Notes]


[Default]

[Reference]


| | |
|-----------|----------|
| [Example] | n = 0x00 |
|-----------|----------|



n = 0x01: Double width



n = 0x02: Double height



n = 0x03: Double width and double height





0x1C 0x71

<FS q>

Logo storage

| Valid for | P3 | | | | | | | | | | |
|---------------|--|----|----|---|---------|---|----------|------|-------------------------------|------|-------------------------------|
| [Format] | Hex | 1C | 71 | m | d1...dk | | | | | | |
| | ASCII | FS | q | m | d1...dk | | | | | | |
| [Range] | m = 0x00, 0x01 0x00 ≤ d ≤ 0xFF | | | | | | | | | | |
| [Description] | Stores a logo in the flash bank specified by m as follows: | | | | | | | | | | |
| | <table><tr><th>m</th><th>FUNCTION</th></tr><tr><td>0x00</td><td>Save logo in the flash bank 1</td></tr><tr><td>0x01</td><td>Save logo in the flash bank 2</td></tr></table> | | | | | m | FUNCTION | 0x00 | Save logo in the flash bank 1 | 0x01 | Save logo in the flash bank 2 |
| m | FUNCTION | | | | | | | | | | |
| 0x00 | Save logo in the flash bank 1 | | | | | | | | | | |
| 0x01 | Save logo in the flash bank 2 | | | | | | | | | | |
| [Notes] | <ul style="list-style-type: none">• The stored logo is a “.bmp” image in Windows bitmap format; a monochrome image (1 bit/pixel) must be used.• The maximum size allowed for the “.bmp” image is 32 kB.• d indicates the byte of the “.bmp” image.• If the value of m is outside the specified range, the data following it are processed as normal data. | | | | | | | | | | |
| [Default] | | | | | | | | | | | |
| [Reference] | | | | | | | | | | | |
| [Example] | | | | | | | | | | | |



PRINT POSITION COMMANDS

0x08

<BS>

Back space

| | | |
|--|-------|----|
| Valid for | P3 | |
| [Format] | Hex | 08 |
| | ASCII | BS |
| [Range] | | |
| [Description] | | |
| Moves print position to previous character. | | |
| [Notes] | | |
| This command can be used to put two characters at the same position. | | |
| [Default] | | |
| [Reference] | | |
| [Example] | | |




0x09

<HT>

Horizontal tab

| | | |
|---------------|--|----|
| Valid for | P3 | |
| [Format] | Hex | 09 |
| | ASCII | HT |
| [Range] | | |
| [Description] | Moves the print position to the next horizontal tab position. | |
| [Notes] | <ul style="list-style-type: none">• Horizontal tab position are set using 0x1B 0x44.• Ignored unless the next horizontal tab position has been set.• If the command is received when the printing position is at the right margin, the device executes print buffer full printing and horizontal tab processing from the beginning of the next line. | |
| [Default] | Default tab positions are set at intervals of 8 characters (9, 17, 25, ...) when the right-side character spacing is 0. | |
| [Reference] | 0x1B 0x44 | |

[Example]





0x1B 0x24

<ESC \$>

Set absolute print position

| | | | | | |
|---------------|--|-----|----|----|----|
| Valid for | P3 | | | | |
| [Format] | Hex | 1B | 24 | nL | nH |
| | ASCII | ESC | \$ | nL | nH |
| [Range] | $0x00 \leq nL \leq 0xFF$ | | | | |
| | $0x00 \leq nH \leq 0xFF$ | | | | |
| [Description] | Sets the distance from the beginning of the line to the position at which subsequent characters are to be printed. | | | | |
| | The distance from the beginning of the line to the print position is $[(nL + nH \times 256) \times (\text{vertical or horizontal motion unit})]$. | | | | |
| [Notes] | • Settings outside the specified printable area are ignored. | | | | |
| | • The horizontal and vertical motion unit are specified by 0x1D 0x50 . | | | | |
| | • 0x1D 0x50 can change the horizontal (and vertical) motion unit. However, the value cannot be less than the minimum horizontal movement amount. | | | | |
| | • In standard mode, the horizontal motion unit (x) is used. | | | | |
| | • If the setting is outside the printing area width, it sets the absolute print position, but the left or right margin is set at default value. | | | | |
| [Default] | | | | | |
| [Reference] | 0x1B 0x5C , 0x1D 0x50 | | | | |
| [Example] | | | | | |



0x1B 0x28 0x76

<ESC (v>

Set relative vertical print position

| | | | | | | |
|---------------|---|-----|----|----|----|----|
| Valid for | P3 | | | | | |
| [Format] | Hex | 1B | 28 | 76 | nL | nH |
| | ASCII | ESC | (| v | nL | nH |
| [Range] | 0x00 ≤ nL ≤ 0xFF 0x00 ≤ nH ≤ 0xFF | | | | | |
| [Description] | Sets the print vertical position based on the current position by using the horizontal or vertical motion unit. This command sets the distance from the current position to [(nL + nH × 256) × horizontal or vertical motion unit]. | | | | | |
| [Notes] | <ul style="list-style-type: none">• When the starting position is specified by N motion unit to the bottom: nL + nH × 256 = N.• When the starting position is specified by N motion unit to the top (negative direction), use the complement of 65536: nL + nH × 256 = 65536 - N.• The horizontal and vertical motion unit are specified by 0x1D 0x50.• The 0x1D 0x50 command can change the horizontal (and vertical) motion unit. However, the value cannot be less than the minimum horizontal movement amount.• In standard mode, the vertical motion unit is used. | | | | | |
| [Default] | | | | | | |
| [Reference] | 0x1D 0x50 | | | | | |
| [Example] | | | | | | |



0x1B 0x44

<ESC D>

Set horizontal tab positions


| | | | | | |
|---------------|--|-----|----|---------|-----|
| Valid for | P3 | | | | |
| [Format] | Hex | 1B | 44 | n1...nk | 00 |
| | ASCII | ESC | D | n1...nk | NUL |
| [Range] | $0x01 \leq n \leq 0xFF$ $0x00 \leq k \leq 0x20$ | | | | |
| [Description] | Sets horizontal tab positions <ul style="list-style-type: none">n specifies the column number for setting a horizontal tab position calculated from the beginning of the line.k indicates the total number of horizontal tab positions to be set. | | | | |
| [Notes] | <ul style="list-style-type: none">The horizontal tab position is stored as a value of [character width × n] measured from the beginning of the line. The character width includes the right-side character spacing and double-width characters are set with twice the width of normal characters.This command cancels previous tab settings.Up to 32 tab positions (k = 0x20) can be set. Data exceeding 32 tab positions is processed as normal data.Send [n] k in ascending order and place a 0 NUL code at the end. When [n] k is less than or equal to the preceding value [n] k-1, the setting is complete and the data which follows is processed as normal data.0x1B 0x44 0x00 cancels all horizontal tab positions.The previously specified horizontal tab position does not change, even if the character width is modified. | | | | |
| [Default] | Default tab positions are set at intervals of 8 characters (columns 9, 17, 25, ...) when the right-side character spacing is 0. | | | | |
| [Reference] | 0x09 | | | | |



[Example]

To set a tabulation to column 4 send the command:

0x1B 0x44 0x03 0x00



To print the string 'ABCD' to the tabulation previously set, the command sequence is:

0x09 'ABCD'

where:

0x09 move the print position to the set horizontal tab (4th column).
'ABCD' is the string to be printed.



0x1B 0x5C

<ESC \>

Set relative print position

| | | | | | |
|---------------|---|-----|----|----|----|
| Valid for | P3 | | | | |
| [Format] | Hex | 1B | 5C | nL | nH |
| | ASCII | ESC | \ | nL | nH |
| [Range] | $0x00 \leq nL \leq 0xFF$ | | | | |
| | $0x00 \leq nH \leq 0xFF$ | | | | |
| [Description] | Sets the print starting position based on the current position by using the horizontal or vertical motion unit. | | | | |
| | Sets the distance from the current position to $[(nL + nH \times 256) \times \text{horizontal or vertical motion unit}]$. | | | | |
| [Notes] | <ul style="list-style-type: none"> • When the starting position is specified by N motion units to the right: $nL + nH \times 256 = N$. • When the starting position is specified by n motion units to the left (negative direction), use the complement of 65536: $nL + nH \times 256 = 65536 - N$. • If setting exceeds the printing area width, the left or right margin is set to the default value. • The horizontal and vertical motion unit are specified by 0x1D 0x50. • 0x1D 0x50 can change the horizontal (and vertical) motion units. However, the value cannot be less than the minimum horizontal movement amount. • In standard mode, the horizontal motion unit is used. • It's possible to print further on the right margin set for every font. In this case the printing continues up to the maximum border of the device mechanism and then begins a new row. | | | | |
| | | | | | |
| | | | | | |
| | | | | | |
| | | | | | |
| | | | | | |
| | | | | | |
| [Default] | | | | | |
| [Reference] | 0x1B 0x24, 0x1D 0x50 | | | | |
| [Example] | | | | | |



0x1B 0x61

<ESC a>

Select justification

| | | | | |
|-----------|----|--|--|--|
| Valid for | P3 | | | |
|-----------|----|--|--|--|

| | | | | |
|----------|-------|-----|----|---|
| [Format] | Hex | 1B | 61 | n |
| | ASCII | ESC | a | n |

| | |
|---------|-------------------------|
| [Range] | $0x00 \leq n \leq 0x02$ |
| | $0x30 \leq n \leq 0x32$ |

[Description] This command selects the type of justification based on the value of n as follows:


| n | JUSTIFICATION |
|------------|---------------------|
| 0x00, 0x30 | Left justification |
| 0x01, 0x31 | Centered |
| 0x02, 0x32 | Right justification |

- [Notes]
- Lines are justified within the specified printing area.
 - Spaces set by 0x09, 0x1B 0x24 and 0x1B 0x5C will be justified according to the previously-entered mode.

[Default] n = 0x00

[Reference]

[Example]






0x1D 0x4C

<GS L>

Set left margin

| | | | | | |
|---------------|---|----|----|----|----|
| Valid for | P3 | | | | |
| [Format] | Hex | 1D | 4C | nL | nH |
| | ASCII | GS | L | nL | nH |
| [Range] | $0x00 \leq nL, nH \leq 0xFF$ | | | | |
| [Description] | Sets the left margin to $[(nL + nH \times 256) \times \text{horizontal motion unit}]$. | | | | |

Area stampabile



- [Notes]
- If the setting exceeds the printable area, the maximum value of the printable area is used.
 - If the left margin + printing area width is greater than the printable area, the printing area width is set at maximum value.
 - The horizontal and vertical motion unit are specified by [0x1D 0x50](#). Changing the horizontal or vertical motion unit does not affect the current left margin.
 - The [0x1D 0x50](#) command can change the horizontal (and vertical) motion unit.
 - However, the value cannot be less than the minimum horizontal movement amount and it must be in even units of the minimum horizontal movement amount.

[Default]

[Reference] [0x1D 0x50](#), [0x1D 0x57](#)

[Example]



0x1D 0x57

<GS W>


Set printing area width

| | | | | | |
|-----------|----|--|--|--|--|
| Valid for | P3 | | | | |
|-----------|----|--|--|--|--|

| | | | | | |
|----------|-------|----|----|----|----|
| [Format] | Hex | 1D | 57 | nL | nH |
| | ASCII | GS | W | nL | nH |

| | |
|---------|--|
| [Range] | $0x00 \leq nL, nH \leq 0xFF$ |
| | $0 \leq (nL + nH \times 256) \leq 640$ |

| | |
|---------------|---|
| [Description] | Sets the printing area width to the area specified by nL and nH. |
| | The left margin is set to $[(nL + nH \times 256) \times (\text{horizontal motion unit})]$ inches. |



| | |
|---------|---|
| [Notes] | • This command is only enabled if set at the beginning of the line. |
| | • If the right margin is greater than the printable area, the printing area width is set at maximum value. |
| | • If the printing area width = 0, it is set at the maximum value. |
| | • The horizontal and vertical motion units are specified by 0x1D 0x50. Changing the horizontal or vertical motion unit does not affect the current left margin. |
| | • The 0x1D 0x50 command can change the horizontal (and vertical) motion unit. However, the value cannot be less than the minimum horizontal movement amount and it must be in even units of the minimum horizontal movement amount. |

[Default]

| | |
|-------------|----------------------|
| [Reference] | 0x1D 0x4C, 0x1D 0x50 |
|-------------|----------------------|

[Example]



MACRO FUNCTIONS CONTROL

0x1D 0x3A

<GS :>

Start or end of macro definition

| | | | |
|----------------------------------|--|----|----|
| Valid for | P3 | | |
| [Format] | Hex | 1D | 3A |
| | ASCII | GS | : |
| [Range] | | | |
| [Description] | | | |
| Starts or ends macro definition. | | | |
| [Notes] | • Macro definition starts when this command is received during normal operation. | | |
| | • When 0x1D 0x5E is received during macro definition, the device ends macro definition and clears all definitions. | | |
| | • Macros are not defined when power is turned on to the machine. | | |
| | • Macro content is not cancelled by the 0x1B 0x40 command. Therefore, 0x1B 0x40 may be included in the content of macro definitions. | | |
| | • If the device receives 0x1D 0x3A a second time after previously receiving 0x1D 0x3A, the device remains in macro undefined status. | | |
| | • The contents of the macro can be defined up to 1024 bytes. If the macro definition exceeds 1024 bytes, excess data is not stored. | | |
| [Default] | | | |
| [Reference] | 0x1D 0x5E | | |
| [Example] | | | |



0x1D 0x5E

<GS ^>

Execute macro

| | | | | | | |
|---------------|---|----|----|---|---|---|
| Valid for | P3 | | | | | |
| [Format] | Hex | 1D | 5E | r | t | m |
| | ASCII | GS | ^ | r | t | m |
| [Range] | 0x00 ≤ r, t ≤ 0xFF 0x00 ≤ m ≤ 0x01 | | | | | |
| [Description] | <p>Executes a macro.</p> <ul style="list-style-type: none">• r specifies the number of times to execute the macro.• t specifies the waiting time for executing the macro. The waiting time is $t \times 100$ ms for each macro execution.• m specifies macro executing mode: When the Least Significant Bit (LSB) of $m = 0$, the macro is executed r times continuously at the interval specified by t. When the Least Significant Bit (LSB) of $m = 1$, after waiting for the period specified by t, the LED indicator blinks and the device waits for the FEED button to be pressed. After the button is pressed, the device executes the macro once. The device repeats the operation r times. | | | | | |
| [Notes] | <ul style="list-style-type: none">• This command has an interval of $(t \times 100$ ms) after a macro is executed by t.• If this command is received while a macro is being defined, the macro definition is aborted and the definition is cleared.• If the macro is not defined or if r is 0x00, nothing is executed.• When the macro is executed by pressing the FEED button ($m = 0x01$), the paper cannot be fed using the FEED button. | | | | | |
| [Default] | | | | | | |
| [Reference] | 0x1D 0x3A | | | | | |
| [Example] | | | | | | |



COMMANDS FOR MECHANISM CONTROL

0x1B 0x6D

<ESC m>

Partial cut

| | | | |
|--|-------|-----|----|
| Valid for | P3 | | |
| [Format] | Hex | 1B | 6D |
| | ASCII | ESC | m |
| [Range] | | | |
| [Description] | | | |
| This command enables autocutter operation and executes a partial cut. | | | |
| [Notes] | | | |
| The device waits to complete all paper movement commands before it executes a partial cut. | | | |
| [Default] | | | |
| [Reference] | | | |
| [Example] | | | |



0x1D 0x56

<GS V>

Select cut mode

| Valid for | P3 | | | | | | | | | |
|---------------|---|----|----|---|---|----------|------------|-------------|------------|---|
| [Format] | Hex | 1D | 56 | m | | | | | | |
| | ASCII | GS | V | m | | | | | | |
| [Range] | m = 0x00, 0x30, 0x41, 0x42 | | | | | | | | | |
| [Description] | Selects cut mode and executes the cut command based on the value of m as follows: | | | | | | | | | |
| | <table><tr><th>m</th><th>FUNCTION</th></tr><tr><td>0x00, 0x30</td><td>Partial cut</td></tr><tr><td>0x41, 0x42</td><td>Form feed (cut position + [n × vertical motion unit]) and partial cut</td></tr></table> | | | | m | FUNCTION | 0x00, 0x30 | Partial cut | 0x41, 0x42 | Form feed (cut position + [n × vertical motion unit]) and partial cut |
| m | FUNCTION | | | | | | | | | |
| 0x00, 0x30 | Partial cut | | | | | | | | | |
| 0x41, 0x42 | Form feed (cut position + [n × vertical motion unit]) and partial cut | | | | | | | | | |
| [Notes] | <ul style="list-style-type: none">• This command is only enabled if set at the beginning of the line.• The horizontal and vertical motion units are specified by 0x1D 0x50. | | | | | | | | | |
| [Default] | | | | | | | | | | |
| [Reference] | 0x1D 0x50 | | | | | | | | | |
| [Example] | | | | | | | | | | |



MISCELLANEOUS COMMANDS

0x1B 0x3D

<ESC =>

Select peripheral device

| | | | | | | | | | | |
|---------------|--|-----------------|----|---|---|----------|------------|----------------|------|-----------------|
| Valid for | P3 | | | | | | | | | |
| [Format] | Hex | 1B | 3D | n | | | | | | |
| | ASCII | ESC | = | n | | | | | | |
| [Range] | 0x01 ≤ n ≤ 0x03 | | | | | | | | | |
| [Description] | Select the device to which the host computer sends data, using n as follows: | | | | | | | | | |
| | <table><tr><td>n</td><td>FUNCTION</td></tr><tr><td>0x01, 0x03</td><td>Device enabled</td></tr><tr><td>0x02</td><td>Device disabled</td></tr></table> | | | | n | FUNCTION | 0x01, 0x03 | Device enabled | 0x02 | Device disabled |
| | n | FUNCTION | | | | | | | | |
| | 0x01, 0x03 | Device enabled | | | | | | | | |
| | 0x02 | Device disabled | | | | | | | | |
| | | | | | | | | | | |
| | | | | | | | | | | |
| | | | | | | | | | | |
| [Notes] | When the device is disabled, it ignores all transmitted data until the device is enabled through this command. | | | | | | | | | |
| [Default] | n = 0x01 | | | | | | | | | |
| [Reference] | | | | | | | | | | |
| [Example] | | | | | | | | | | |



0x1B 0x40

<ESC @>

Initialize device

| | | | |
|--|-------|-----|----|
| Valid for | P3 | | |
| [Format] | Hex | 1B | 40 |
| | ASCII | ESC | @ |
| [Range] | | | |
| [Description] | | | |
| Clears the data in the print buffer and resets the device mode to that in effect when power was turned on. | | | |
| [Notes] | | | |
| <ul style="list-style-type: none">• The data in the receiver buffer is not cleared.• The macro definitions are not cleared. | | | |
| [Default] | | | |
| [Reference] | | | |
| [Example] | | | |



0x1B 0x63 0x35

<ESC c 5>

Enable or disable keys panel

| | | | | | |
|---------------|--|-----|----|----|---|
| Valid for | P3 | | | | |
| [Format] | Hex | 1B | 63 | 35 | n |
| | ASCII | ESC | c | 5 | n |
| [Range] | $0x00 \leq n \leq 0xFF$ | | | | |
| [Description] | Enables or disables the keys panel, based on the value of n - when the Least Significant Bit (LSB) of n is 0, the keys panel is enabled. - when the Least Significant Bit (LSB) of n is 1, the keys panel is disabled. | | | | |
| [Notes] | <ul style="list-style-type: none">• Only the Least Significant Bit (LSB) of n is effective.• When the keys panel is disabled, the keys may only be used after the device has been reset. | | | | |
| [Default] | n = 0x00 | | | | |
| [Reference] | | | | | |
| [Example] | | | | | |



0x1B 0x70

<ESC p>

Generate pulse on drawer connector

| Valid for | P3 | | | | | | | | | | | |
|---------------|--|-----|----|---|----|----|---|---------------|------------|---|------------|---|
| [Format] | Hex | 1B | 70 | m | t1 | t2 | | | | | | |
| | ASCII | ESC | p | m | t1 | t2 | | | | | | |
| [Range] | m = 0x00, 0x01, 0x30, 0x31 0x00 ≤ t1 ≤ 0xFF 0x00 ≤ t2 ≤ 0xFF | | | | | | | | | | | |
| [Description] | Outputs the pulse of duration t1 + t2 to cash drawer connector pin specified by m as follows: <table><tr><th>m</th><th>CONNECTOR PIN</th></tr><tr><td>0x00, 0x30</td><td>Drawer kick-out connector pin 2 (cash drawer 2)</td></tr><tr><td>0x01, 0x31</td><td>Drawer kick-out connector pin 2 (cash drawer 1)</td></tr></table> | | | | | | m | CONNECTOR PIN | 0x00, 0x30 | Drawer kick-out connector pin 2 (cash drawer 2) | 0x01, 0x31 | Drawer kick-out connector pin 2 (cash drawer 1) |
| m | CONNECTOR PIN | | | | | | | | | | | |
| 0x00, 0x30 | Drawer kick-out connector pin 2 (cash drawer 2) | | | | | | | | | | | |
| 0x01, 0x31 | Drawer kick-out connector pin 2 (cash drawer 1) | | | | | | | | | | | |
| [Notes] | <ul style="list-style-type: none">• The pulse ON time is (t1 × 2) ms and the pulse OFF time is (t2 × 2) ms.• If t2 < t1, the OFF time is (t1 × 2) ms. | | | | | | | | | | | |
| [Default] | | | | | | | | | | | | |
| [Reference] | | | | | | | | | | | | |
| [Example] | | | | | | | | | | | | |



0x1D 0x49

<GS />

Transmit device ID

| | |
|-----------|----|
| Valid for | P3 |
|-----------|----|

| | | | | |
|----------|-------|----|----|---|
| [Format] | Hex | 1D | 49 | n |
| | ASCII | GS | I | n |

| | |
|---------|-----------------|
| [Range] | 0x01 ≤ n ≤ 0x03 |
| | 0x31 ≤ n ≤ 0x33 |
| | n = 0xFF |

| | |
|---------------|---|
| [Description] | Transmits the device ID specified by n follows: |
|---------------|---|

| n | DEVICE ID | SPECIFICATION |
|------------|---------------------------|---|
| 0x01, 0x31 | Device model ID (1 byte) | 0xFF (resend the command with n = 0xFF) |
| 0x02, 0x32 | Type ID | See table below |
| 0x03, 0x33 | ROM version ID (4 bytes) | Depends on ROM version (4 character) |
| 0xFF | Device model ID (2 bytes) | 0x02 0x60 |

n = 0x02, 0x32 Type ID

| BIT | OFF/ON | HEX | FUNCTION |
|-----|--------|-----|--|
| 0 | Off | 00 | 2 bytes characters codes not supported |
| 1 | Off | 00 | Autocutter not supplied |
| | On | 02 | Autocutter supplied |
| 2 | Off | 00 | Thermal paper w/o label |
| | On | 04 | Thermal paper label |
| 3 | - | - | Undefined |
| 4 | Off | 00 | Not used. Fixed to off |
| 5 | - | - | Undefined |
| 6 | - | - | Undefined |
| 7 | Off | 00 | Not used. Fixed to off |

| | |
|---------|--|
| [Notes] | This command is executed when the data is processed in the data buffer. Therefore, there could be a time lag between command reception and data transmission, depending on data buffer status. |
|---------|--|

[Default]

[Reference]

[Example]



0x1D 0x50

<GS P>

Set horizontal and vertical motion units

| | | | | | |
|---------------|--|----|----|---|---|
| Valid for | P3 | | | | |
| [Format] | Hex | 1D | 50 | x | y |
| | ASCII | GS | P | x | y |
| [Range] | 0x00 ≤ x, y ≤ 0xFF | | | | |
| [Description] | <p>Sets the horizontal and vertical motion units to 1/x inch and 1/y inch respectively.</p> <p>When x is set to 0, the default setting value is used.</p> <p>When y is set to 0, the default setting value is used.</p> | | | | |
| [Notes] | <ul style="list-style-type: none">• The horizontal direction is perpendicular to the paper feed direction.• In standard mode, the following commands use x or y, regardless of character rotation (upside-down or 90° clockwise rotation): <p>Commands using x: 0x1B 0x20, 0x1B 0x24, 0x1B 0x5C, 0x1D 0x4C, 0x1D 0x57.</p> <p>Commands using y: 0x1B 0x33, 0x1B 0x4A.</p> <ul style="list-style-type: none">• This command does not affect the previously specified values.• The calculated result from combining this command with others is truncated to the minimum value of the mechanical pitch or an exact multiple of that value. | | | | |
| [Default] | x = 0xCC, y = 0xCC | | | | |
| [Reference] | 0x1B 0x20, 0x1B 0x24, 0x1B 0x5C, 0x1B 0x33, 0x1B 0x4A, 0x1D 0x4C, 0x1D 0x57 | | | | |
| [Example] | | | | | |



0x1D 0xE6

Virtual paper end limit

| | | | | | |
|---------------|--|----|------|----|----|
| Valid for | P3 | | | | |
| [Format] | Hex | 1D | E6 | nH | nL |
| | ASCII | GS | 0xE6 | nH | nL |
| [Range] | $0x00 \leq nH \leq 0xFF$ | | | | |
| | $0x00 \leq nL \leq 0xFF$ | | | | |
| [Description] | This command sets the limit, expressed in cm as $[(nH \times 256) + nL]$, after which is pointed out the virtual paper-end. | | | | |
| [Notes] | | | | | |
| [Default] | nH = 0x00 | | | | |
| | nL = 0xF0 | | | | |
| [Reference] | | | | | |
| [Example] | To see the virtual paper-end is pointed out after 15 metres from the first detection of low paper, it's necessary convert 15 metres in 1500 centimetres and then, calculate nH and nL value in the following mode: | | | | |
| | $nH = 1500 / 256 = 5$ | | | | |
| | $nL = 1500 - (nH \times 256) = 1500 - (5 \times 256) = 220$ | | | | |
| | and then send the following command: | | | | |
| | 0x1D 0xE6 0x05 0xDC | | | | |



0x1D 0xE9

Set minimum ticket length

| | | | | |
|---------------|--|----|------|---|
| Valid for | P3 | | | |
| [Format] | Hex | 1D | E9 | n |
| | ASCII | GS | 0xE9 | n |
| [Range] | $0x00 \leq n \leq 0xFF$ | | | |
| [Description] | This command sets the minimum ticket length to the n value. | | | |
| [Notes] | | | | |
| [Default] | 45 mm | | | |
| [Reference] | | | | |
| [Example] | To set the minimum ticket length at 56 mm, the command sequence is: 0x1D 0xE9 0x00 0x38 | | | |



0x1D 0xF0

Set print mode

| | | | | | | | | | | | | |
|---------------|--|--------------|------|---|---|------------|------|--------------|------|--------|------|------------|
| Valid for | P3 | | | | | | | | | | | |
| [Format] | Hex | 1D | F0 | n | | | | | | | | |
| | ASCII | GS | 0xF0 | n | | | | | | | | |
| [Range] | 0x00 ≤ n ≤ 0x02 | | | | | | | | | | | |
| [Description] | Sets print mode based on the value of n as follows: | | | | | | | | | | | |
| | <table><tr><td>n</td><td>PRINT MODE</td></tr><tr><td>0x00</td><td>High quality</td></tr><tr><td>0x01</td><td>Normal</td></tr><tr><td>0x02</td><td>High speed</td></tr></table> | | | | n | PRINT MODE | 0x00 | High quality | 0x01 | Normal | 0x02 | High speed |
| | n | PRINT MODE | | | | | | | | | | |
| | 0x00 | High quality | | | | | | | | | | |
| | 0x01 | Normal | | | | | | | | | | |
| | 0x02 | High speed | | | | | | | | | | |
| [Notes] | Print mode reverts to the default value when the device is reset or turned off. | | | | | | | | | | | |
| [Default] | n = 0x02 | | | | | | | | | | | |
| [Reference] | | | | | | | | | | | | |
| [Example] | | | | | | | | | | | | |



CUSTOM S.p.A.

World Headquarters

Via Berettine, 2/B - 43010 Fontevivo, Parma ITALY

Tel. +39 0521 680111 - Fax +39 0521 610701

info@custom.biz - www.custom.biz

All rights reserved

www.custom.biz